2006

Modeling and fabrication of a microthermocouple array

Adam Cygan

Louisiana State University and Agricultural and Mechanical College

Follow this and additional works at: https://digitalcommons.lsu.edu/gradschool_theses

Part of the [Mechanical Engineering Commons](#)

Recommended Citation

Cygan, Adam, "Modeling and fabrication of a microthermocouple array" (2006). *LSU Master's Theses*. 1526.

https://digitalcommons.lsu.edu/gradschool_theses/1526

This Thesis is brought to you for free and open access by the Graduate School at LSU Digital Commons. It has been accepted for inclusion in LSU Master's Theses by an authorized graduate school editor of LSU Digital Commons. For more information, please contact gradetd@lsu.edu.

MODELING AND FABRICATION
OF A MICROTHERMOCOUPLE ARRAY

A Thesis

Submitted to the Graduate Faculty of the
Louisiana State University and
Agricultural and Mechanical College
in partial fulfillment of the
requirements for the degree of
Master of Science in Mechanical Engineering

in

The Department of Mechanical Engineering

by
Adam Cygan
B.S., Louisiana State University, 2002
May 2006

Acknowledgements

I would like to thank all of the people that helped me get through this project. There were definitely a lot of them, and it would not be possible without the aid of everyone involved both directly and indirectly. I want to especially thank my advisor, Dr. Murphy for his all his help, and especially for encouraging me when I felt hopeless. I also want to thank the people on my committee for their assistance in the project. Dr. Podlaha's help with the electrodeposition was invaluable, and she was always ready to talk. Dr. Devireddy was always eager to explain something when I had a confusion about cell freezing or especially on aspects of the cooling stage. Dr. Ekkad provided help with the modeling aspect of the research.

Dr. Park helped a great deal with his knowledge of microfabrication, and his insightful comments were always useful in determining what I should do next or how I should work out a particular problem. Without his help, I'm not sure how I would have been able to tackle the microfabrication. Don Patterson helped tremendously and did all of the instrumentation work required in the project. I would like to thank Yohannes Desta and Abhinav Bhushan for giving advice in microfabrication, and Fareed Dawan for always helping with the e-beam deposition. Dr. Xie at the Geology department was very helpful and friendly in helping me to use the SEM to take pictures and analyze sample composition. Paul and Fred at the Chemical engineering shop helped in different fabrication aspects, such as the plating jig, and they were always ready to make fun of me.

Of course I can't forget all the guys in the lab, who were always able to consistently help distract me when I needed it. Diwakar, Pin Chuan, Chetan, Kevin, Taehyun, Namwon, Byoung Hee, Taeyoon, and Chris; I can't tell you how much I appreciate having you around. I'm going to miss you guys. I want to also thank the other people working on freezing things, Aparna, Ajay, Dinesh. I learned a lot from you.

My family has been wonderful this whole time, and sometimes I wonder how they put up with me. My mom and dad, my wife, my sister, my grandparents, and everyone have really helped me to make it through all of the hard work.

I also want to thank CAMD for the use of their facilities to do the microfabrication. Finally, I would like to acknowledge the National Science Foundation, which helped to fund my graduate studies.

Table of Contents

Acknowledgements.....	ii
Abstract.....	viii
1. Introduction.....	1
1.1. Cryobiology.....	1
1.2. Motivation.....	1
1.2.1. Cryosurgery.....	1
1.2.2. Cryopreservation.....	2
1.3. Proposed Device.....	3
1.3.1. Objective.....	3
1.3.2. Approach.....	4
1.4. Future Chapters.....	5
2. Background.....	7
2.1. Cellular Response to Freezing.....	7
2.1.1. Dehydration with Intracellular Ice Formation.....	7
2.1.2. Solution Effects.....	8
2.1.3. Cell Warming and Recrystallization.....	9
2.1.4. Tissue Response to Freezing.....	9
2.1.5. Release of Energy as Cells Freeze.....	9
2.2. Developments in Cryobiology.....	10
2.2.1. Maximizing Cell Survival.....	10
2.2.2. Observing and Quantifying Freezing Effects on Cells.....	11
2.2.3. Cell and Tissue Models.....	13
2.2.4. Experimental Tissue Dehydration Data.....	13
2.2.5. Experimental Tissue Freezing Data.....	14
2.3. Thermocouples.....	15
2.3.1. Introduction.....	15
2.3.2. Thermocouple Laws.....	18
2.3.3. Reliability and Sources of Error.....	19
2.3.4. Transient Temperature Measurement Considerations.....	21
2.3.5. EMF Measurement.....	22
2.3.6. Installation Effects.....	22
2.3.7. Reference Junctions.....	23
2.3.8. Calibration.....	23
2.3.9. Microthermocouples.....	24
3. Thermal Modeling.....	27
3.1. Background.....	27
3.1.1. Objective.....	27
3.1.2. Experimental Apparatus.....	27
3.2. Device Requirements.....	29
3.3. Methods and Calculations.....	30

3.3.1. Preliminary Models.....	30
3.3.2. Finite Element Modeling.....	31
3.3.2.1. Assumptions.....	31
3.3.2.1.1. Thermoelectric Effects.....	31
3.3.2.1.2. Latent Heat Release of Cells.....	32
3.3.2.2. Geometry.....	33
3.3.2.3. Cell Size and Thermocouple Spacing.....	33
3.3.2.2.2. Model Simplification.....	33
3.3.2.2.3. Effects of Thermocouples on the System.....	34
3.3.2.2.4. Tolerance and Fabrication Limits.....	36
3.3.2.3. Boundary Conditions.....	36
3.3.2.6. Material Properties.....	37
3.3.2.5. Meshing.....	38
3.3.2.6. Cooling Rate.....	39
3.3.2.7. Cell freezing Time.....	40
3.3.2.8. Thermocouples.....	42
3.4. Results.....	43
3.4.1. Thermocouple Effects on the System.....	43
3.4.2. Thermocouple Isolation.....	45
3.4.3. Cell Placement and Thermocouple Spacing Effects.....	48
3.4.5. Result Verification.....	51
3.4.5.2. Mesh and Time Step Refinement.....	51
3.4.5.3. Geometry and Material Variation.....	53
3.5. Discussion.....	54
4. Fabrication.....	58
4.1. Background.....	58
4.2. Fabrication Outline.....	59
4.3. Resist Parameter Optimization.....	60
4.4. Tolerance Analysis.....	62
4.4.1. Background.....	63
4.4.2. Description of Analysis.....	63
4.4.3. Post Alignment Testing.....	69
4.5. Electrodeposition.....	72
4.5.1. Background.....	72
4.5.2. Copper-Nickel Deposition Background.....	77
4.5.3. Plating in Recesses.....	78
4.5.4. Plating Along the Surface Uniformly.....	79
4.5.4.1. Electric Field Lines.....	79
4.5.4.2. Wagner Number.....	80
4.5.4.3. Active Area Density.....	81
4.5.4.4. Auxiliary Electrode.....	81
4.5.5. Electrodeposition Experiments.....	83
4.5.5.1. Flat Plate Deposition Testing.....	83
4.5.5.2. Rotating Hull Cell Testing.....	85

4.5.5.2.1. Background.....	85
4.5.5.2.2. Testing.....	86
4.5.5.3. Wiring Deposition Testing.....	91
4.6. Mask Design.....	93
4.6.1. Mask Concerns and Design Goals.....	93
4.6.2. Alignment Marks.....	94
4.6.3. Current Uniformity Along Substrate Surface.....	95
4.7. Device Fabrication.....	96
4.7.1. Wafer Preparation.....	96
4.7.2. Wiring Layer.....	96
4.7.3. Post Layer.....	99
4.7.4. Junction Layer.....	103
4.7.5. Etching the Plating Base.....	104
4.8. Conclusions.....	106
5. Calibration and Testing.....	109
5.1. Instrumentation.....	109
5.1.1. Amplifiers and Multiplexing.....	110
5.1.2. Reference Junction Compensation.....	112
5.1.3. Noise Filtering.....	113
5.1.4. Data Acquisition.....	113
5.2. Thermocouple Calibration.....	114
5.2.1. Sources of Error.....	114
5.2.1.1. Nonuniformity in Wires.....	114
5.2.1.2. Standard Reference Thermocouple.....	116
5.2.1.3. Adhesion Layer and Seed Layer.....	117
5.2.2. Calibration Procedure.....	119
5.2.3. Calibration Results.....	121
5.2.3. Conclusions.....	124
6. Conclusions and Future Work.....	126
6.1. Modeling.....	126
6.1.1. Conclusions.....	126
6.1.2. Future Work.....	127
6.2. Fabrication.....	128
6.2.1. Conclusions.....	128
6.2.2. Future Work.....	129
6.3. Calibration and Testing.....	130
6.3.1. Conclusions.....	130
6.3.2. Future Work.....	131
References.....	132
Appendix A: Photomasks Used in Microfabrication.....	138
Appendix B: Microthermocouple Testing Results.....	143

Appendix C: Circuit Diagram.....	152
Vita.....	156

Abstract

Cryobiology is the study of how living cells and tissues respond to freezing and exposure to subzero temperatures. Studies in this field are aimed toward improving methods of cryosurgery as well as the storage of cells and tissues. For example, one area of research is to link the biophysical cellular dehydration and intracellular ice formation in cells during tissue freezing to cell viability and mechanical properties after thawing. There is currently a method for measuring dehydration in cells as part of a tissue, but not an adequate method for measuring intracellular ice formation in tissues.

A prototype device that would allow measurement of intracellular ice formation by measuring the heat release of individual cells during freezing with an array of type-T microthermocouples was fabricated and tested. The device was designed to consist of a microfabricated wiring layer with an intermediate post layer to improve thermal insulation, and a rectangular junction layer to connect the two metals of the thermocouple.

Modeling was used to determine the most suitable geometries for the device. Posts of 3 μm and 5 μm in diameter were modeled, with heights of 20 μm and 50 μm , as well as a wiring layer without posts. For both heights tested, the 3 μm posts improved the thermocouple response over a no post case, while 5 μm posts gave inferior results. Interference between adjacent thermocouples was found to be negligible as long as a cell was in contact with a thermocouple junction.

A multilayer UV-LIGA process on a silicon wafer substrate with an E-beam deposited seed layer was used to fabricate the device. Electrodeposition was used to fabricate the wiring, posts, and junctions for the thermocouples. The seed layer was then etched away to provide electrical insulation between individual thermocouples.

The microfabricated device was connected to a custom made PC board with multiplexing, amplifying and filtering circuitry. In initial tests, the thermocouple array showed a trend of voltage variation with temperature, indicating a working thermocouple array. Future work to more adequately characterize the performance is presented.

1. Introduction

1.1. Cryobiology

Cryobiology is the study of how living cells and tissues respond to freezing and exposure to subzero temperatures. This includes both the freezing and subsequent thawing of a biological system. The following chapter provides some background into the motivation for this project along with a brief summary of what was accomplished.

1.2. Motivation

1.2.1. Cryosurgery

Cryosurgery uses controlled, localized freezing temperatures to selectively destroy tumorous tissues to treat patients with cancer. It is beneficial because it allows for a minimally invasive procedure that is quicker than conventional surgical methods.

Cryosurgery is developing, and work is being done to improve procedures. Problems that are faced include ensuring that the ice from the surgical probe is spreading at the proper rate and can be adequately monitored. A better understanding of the biophysical mechanisms of tissue freezing are also needed (Bischof, 2000). Better visualization of ice formation in surgery has been addressed through techniques including ultrasound and magnetic resonance imaging (Tacke, et al., 1999; Rubinsky, et al., 1993). However, it is clear that a strong understanding of events that take place in biological systems during the freezing process and how they relate to the conditions of cells afterwards is necessary to identify the most effective procedures.

1.2.2. Cryopreservation

There is an organ shortage in the United States. According to the United Network of Organ sharing, this is the most significant issue facing the transplant community. At the end of 2003, over 86,000 people were on the waiting list for receiving an organ or tissue transplant, and only 13,275 people donated organs or tissues that year. Over 7,000 people died waiting for organs in 2003 (OPTN/SRTR, 2004).

One of the solutions being considered is tissue engineering, or the creation of artificial tissues for transplant and regeneration in patients. Many advances have been made in the field, but it is still necessary to be able to store these tissues for extended periods of time before they can be transplanted into patients. Cryopreservation is one proposed solution to this problem.

Cryopreservation aims to keep living cells, tissue, and ultimately organs alive for prolonged periods through carefully controlled freezing and thawing. When a cell or tissue culture is subjected to a cooling rate, the surrounding extracellular fluid tends to freeze first. As parts of the extracellular fluid freeze, the remaining fluid becomes more concentrated with solute. The water inside the cells, still unfrozen, will leave the cell in order to try and equilibrate the intracellular and extracellular solute concentrations. This is known as cellular dehydration. When the temperature reaches a certain point, based on the cooling rate, cell type and other factors, if there is any water remaining within a cell, it will freeze. This is known as intracellular ice formation (IIF). Both IIF and cellular dehydration have been shown to be harmful to the survival of cells after

thawing (Mazur, 1970). The balance of these two phenomenon characterizes the freezing history of the cell or tissue sample.

There are two main issues that need to be resolved in cryopreservation (Bischof, 2000). Firstly, cryopreservation requires the use of cryoprotective agents (CPAs), which are easy to insert into cells but difficult to administer uniformly to tissues. Research is being done with NMR spectroscopy and microscopic analysis to analyze CPA penetration into tissues (Isbell, et al., 1997; Fuller, et al., 1989). Additionally, ice formation and dehydration need to be optimized.

The problem of measuring and monitoring cellular dehydration in tissues has been addressed through the use of calorimetry (Devireddy and Bischof, 2003) and freeze substitution (Pazhayannur and Bischof, 1997). However, there is currently not an adequate method for measuring IIF in cells as part of a tissue culture. Although modeling has been developed (Bischof and Rubinsky, 1993; Devireddy, et al., 2002), there is a lack of experimental data to validate the models of cell freezing in tissues. In order to maximize the usability of cryopreservation, it is important to understand all of the phenomena occurring in a tissue system during freezing.

1.3. Proposed Device

1.3.1. Objective

The goal of the device is to be able to relate post thaw viability and mechanical properties to the freezing history, defined as the interaction of IIF and cellular dehydration, of cell and tissue cultures. An array of micro thermocouples

is proposed to monitor individual cells during cooling, in order to determine when ice formation occurs in cells.

When a cooling rate is applied to tissues, and cells freeze, there is a brief temperature increase in the cell due to the release of the latent heat of fusion during ice formation. If a device can monitor individual cell temperature, the time of occurrence of the temperature jump in each cell will be known. This translates to knowledge of when each cell freezes, so that there can be a record of the time history of freezing of the cell matrix sample. Combined with data on the dehydration of the cells during freezing, which can be obtained with another sample under the same conditions, the entire picture of what takes place during the cooling process can be related to the cell survival rate and the post thaw mechanical properties. This can lead to a better understanding of the freezing process in tissues, and provide valuable data for future work in the field of cryopreservation and cryosurgery.

It is generally an easy task to monitor freezing in individual cells, since the cells can be observed directly under a microscope. Freezing in cells that are part of a tissue is more difficult, however, because they are not always translucent and cannot always be easily visualized. This means that another method must be used to detect the ice formation.

1.3.2. Approach

This work was intended to lay the foundation for future generations of sensor arrays. Making the prototype first allowed more focus on the design issues without serious problems in instrumentation and data acquisition, and also

allowed testing of different thermocouple geometries on a single wafer. Two sets of arrays of 9 (3x3) type-T thermocouples, with different geometries and center-to-center spacing for both sets of arrays, were fabricated. A cell culture will be placed directly above the thermocouple junctions, and a cooling stage placed below the device. As a cooling rate is applied, the thermocouple array will monitor the freezing of cells within the culture. The thermal response of the device was modeled, and a proof of concept prototype was fabricated and tested.

A second generation device will have an array of 100 (10x10) type-T thermocouples spaced at 50 μm apart to measure temperature in the neighborhood of a single cell. A third generation device will include thermoelectric coolers interspersed within the thermocouple array allowing modulation of temperature around individual cells. Although the coolers are not able to provide a very large change in temperature, and external cooling is still required, they will provide information about cellular response to local temperature input, and this would help to control freezing of individual cells.

1.4. Future Chapters

One of the main concerns in designing the device was ensuring that each thermocouple can indeed register individual cell temperature without being significantly influenced by neighboring cells. Chapter 3 presents the finite element modeling that has been done for this device to help in the design phase.

The fabrication of the prototype device was done through a multi-step photolithography process. Many factors were involved in fabrication, including mask fabrication, alignment, tolerancing issues, electroplating parameters, and

UV exposure times. The research and testing that has been done as well as the steps used to fabricate are included in Chapter 4.

To calibrate the device, voltage responses were recorded from several of the microthermocouples for a range of different temperatures. Calibration curves were formulated from the data, although the results were inconclusive, and require more testing. After successful calibration, the device can then be used to monitor freezing in cell tissue cultures. Chapter 5 presents information on the calibration and testing of the device in greater detail. Chapter 6 gives conclusions reached and recommendations for future work.

2. Background

This chapter is intended to provide some information on the nature of cell and tissue freezing phenomena, along with a review of some of the experiments and modeling that have been done in the field. The final section will touch upon thermocouple theory and micro temperature sensing devices developed in the past.

2.1. Cellular Response to Freezing

It is important to understand that there are differences between simple cell effects and tissue effects during the freezing process. Most research has focused on the cell response, and data on tissue response have been more limited (Bischof, 2000).

2.1.1. Dehydration with Intracellular Ice Formation

As a cell culture is subjected to a cooling rate, several complex phenomena occur that make this process interesting to study and difficult to fully predict and understand. The extracellular matrix of fluid around the cells will tend to freeze first, before the water inside individual cells freezes. This means that the water in the cell supercools, or exists below its normal freezing point, but eventually, when the temperature is low enough (often between -10°C and -15°C), ice will form inside the cell (Mazur, 1965). This is known as intracellular ice formation (IIF).

As parts of the extracellular fluid freeze, and the fluid inside the cells remains unfrozen, the difference in vapor pressure between the interior and exterior of the cell causes them to lose water to their surroundings (Mazur, 1970).

As water leaves the cell, solute concentration inside the cell increases, lowering the vapor pressure in order to reach equilibrium. This phenomenon is known as cellular dehydration. The rate of this dehydration is governed mainly by the cooling rate and the permeability of the cell membrane to water (Mazur, 1963). An interesting effect of this dehydration of cells is that there is a *critical cooling rate*, above which ice formation occurs inside a cell, and below which, there is (virtually) no ice formation inside the cell because the liquid leaves the cell before ice can form (Mazur, 1970). The importance of this critical cooling rate is that ice formation in cells has been shown to be damaging and even lethal (Mazur, 1970).

2.1.2. Solution Effects

As water leaves the cell, the solute concentration inside the cell increases, solute begins to precipitate, and the pH of the solution increases. Ultimately, all solutes would precipitate before the water in the cell freezes (Mazur, 1970). The amount of precipitation is dependant on the temperature of the system at a constant pressure, as long as vapor pressure equilibrium can be achieved (Mazur, 1970). Since solute concentration inside the cell is increased, the rate of cooling affects how long the cell will be subjected to a more highly concentrated solution. It has been shown experimentally that an increased solution concentration can be damaging to cells (Lovelock, 1953). The faster the cooling rate, the shorter the amount of time the cell will experience this exposure.

2.1.3. Cell Warming and Recrystallization

Once the cell is completely frozen, it is still possible for it to become damaged through ice grain growth and recrystallization. If a cell culture is frozen rapidly, it creates small ice crystals, which can unite when warmed again and form larger crystals to reduce surface energy (Menz and Luyet, 1961). The most dramatic recrystallization occurs when the warming is slow (Mazur, 1970). In studies done on several kinds of cells, the growth of ice crystals was shown to be more damaging than their formation (Mazur, 1970). It has been hypothesized that the lipids in cell membranes can start to leak due to solution effects. These leaks can cause the cell to flood with solution on warming, damaging or destroying the cell (Mazur, 1970).

2.1.4. Tissue Response to Freezing

Tissue freezing is similar to single cell freezing, in the sense that both cellular dehydration and IIF occur, but there are a few differences. During dehydration, in addition to the increase in solute concentration, cells that are part of tissues can be damaged from shrinkage of channels of unfrozen medium that form in tissue where cells reside (Mazur, 1984). Ice tends to form more easily in cells that are part of a tissue than in individual cells, because of cell to cell interactions (Irimia and Karlsson, 2002). In addition, it is difficult to uniformly freeze and distribute cryoprotective agents throughout the tissue (Bischof, 2000).

2.1.5. Release of Energy as Cells Freeze

One other phenomenon occurring when cells freeze or when any aqueous solution freezes, is the release of energy upon freezing, and the accompanying

temperature increase in the immediate surroundings. When water crystallizes, it releases energy from the latent heat of fusion. The amount of energy released is based on the mass of water that is frozen, and the temperature at which this freezing occurs. The released energy heats the cell and the immediate surroundings. This insight will be applied in the current project.

2.2. Developments in Cryobiology

There have been many advances in the field of cryobiology that have lead to promising developments in the field. The goal of much of this work is to get a better understanding of the events that take place in cells and tissues during the freezing and thawing process, as well as relate post cell viability to cellular events during freezing. These next sections will detail some of the work that has been done in this area.

2.2.1. Maximizing Cell Survival

During the freezing process there are several opportunities for cells to be damaged and killed. As discussed earlier, two main events, IIF and solution effects cause damage in cells. Ice formation in the cell occurs when the cooling rate is fast, and water does not have a chance to leave the cell before freezing occurs. If cooling is too slow, however, cells can be damaged by high concentrations of solutes remaining in the cell due to dehydration, and also in tissues from shrinkage of channels around the cell. Since both events are affected by the cooling rate in a different way, there tends to be an optimum cooling rate that balances the effects of these two phenomena (Mazur, 1970).

The rate is different for different cells, depending on cell size and its permeability to water.

One tool used to aid cells in survival of freezing temperatures is the cryoprotective agent (CPA). For some cells, cooling rates that are low enough to prevent IIF are also slow enough to give cells dangerous exposure to solution effects, and there is therefore no optimum cooling rate (Mazur, 1970). In order to improve this situation, protective additives such as glycerol or dimethyl sulfoxide may be added to the cells (Mazur, 1970). The CPAs work by reducing the amount of damaging electrolytes in unfrozen portions of the cell and therefore lessening the damage from solution effects (Mazur, 1970). The task of loading the CPA before freezing and unloading it after thawing is important to minimize damage to cells. Applying CPAs to individual cells is a relatively simple matter, but applying CPAs to tissue samples can be more complicated, and the problem has not been completely solved for larger tissue systems (Bischof, 2000).

2.2.2. Observing and Quantifying Freezing Effects on Cells

The study of cryobiology involves interesting engineering challenges because of the nature of the science. The part of the system that needs to be observed, the cells, are very small (around 30 μm diameter), and the temperatures that are being used can be as low as $-196\text{ }^{\circ}\text{C}$. In addition, when tissues are involved, visual observation becomes more difficult. The past developments in the field of observational devices are important in understanding future needs for devices to study freezing effects.

The development of the cryomicroscope stage by Sachs was an important advancement in cell freezing analysis (Diller, 1997). The device consisted of a cooling stage with a microscope that allowed visualization of cells and cellular dehydration. Molisch made a similar device and was able to study dehydration as well as IIF (Diller, 1997). The studies of Sachs and Molisch were significant, but were also mainly qualitative observations of cellular phenomena. Diller and Cravalho (1970) developed a cryomicroscope that could give precise control of cooling rates. Walcerz (1991) modified the design to allow CPAs to be added during the execution of freezing protocols to get a better understanding of their effect. Another development came through a device that had a moveable stage to follow the freeze front under a microscope for viewing. This allowed for viewing of large specimens and also for better, longer analysis of the freezing process itself (Diller, 1997).

These microscopes work very well for observing cellular freezing and dehydration effects. IIF can be observed simply as a change in color or texture of a cell optically, and dehydration can be observed through cell shrinkage, although simply observing shrinkage can lead to some inaccuracies, since the image is not three dimensional and cell boundaries can be hard to accurately see through extracellular ice (Diller, 1997). The main concern for tissue studies is that they can often be thick, and not as translucent to light, thus not allowing simple visual observations of a sample. The study of tissues has therefore been more recent, and developments in that field are detailed separately.

2.2.3. Cell and Tissue Models

Several groups have developed mathematical models to predict cell behavior under varying conditions. The first, most prominent, model was developed by Mazur for water transport in single cell freezing (Mazur, 1963). Levin, et al. (1976) modified Mazur's model and improved the temperature dependent simulation of cell permeability. Pitt, et al. (1992) developed a statistical model to predict intracellular ice formation in a large variety of cells under several conditions. Toner, et al. (1990) developed a more detailed model to predict ice formation in cells coupled with cellular dehydration. Later, Karlsson, et al. (1994) developed a model of ice crystallization within a single cell that also took into account the effect of CPAs as well as the growth of intracellular ice crystals.

Several models have also been developed to predict cell behavior as part of a tissue during freezing. Rubinsky and Pegg (1988) created a model to predict cellular dehydration in biological tissues that combines the well known Krogh Cylinder model for mass transport and Mazur's single cell freezing model. Bischof and Rubinsky (1993) developed a model that also included IIF. An improved model was more recently developed by Devireddy, et al. (2002) that uses a coupled thermal/biophysical approach to study heat and mass transport in tissues during freezing.

2.2.4. Experimental Tissue Dehydration Data

With such tissue models available, it is important to be able to run experiments to test the data from them. A few experiments have been performed

to monitor cell dehydration in tissue samples. Pazhayannur and Bischof (1997) used a directional solidification method followed by freeze substitution to get data on cell dehydration during the cooling process. In directional solidification, a stage is moved between two blocks at different temperatures, T_{high} and T_{low} . By varying the velocity of the stage, a constant cooling rate can be achieved.

The procedure of Pazhayannur and Bischof was a two-step method. The first step was cooling the sample to an intermediate temperature, where dehydration still occurred, and then immediately slam freezing to give a “snapshot” of what the system looked like at a certain temperature, given a certain cooling rate. Slam freezing means the sample was put into contact with a very cold conductive block that freezes the sample with a cooling rate over 1000 °C/min. The next step was freeze substitution, where frozen sections were replaced with resin to facilitate analysis. After performing several experiments, with each sample cooled at the same rate, but to a different intermediate temperature before slam freezing, the data were analyzed to determine the dehydration characteristics of the tissue samples.

A second method was tested by Devireddy and Bischof (1998). This method used differential scanning calorimetry (DSC) to measure the heat release of a tissue system during freezing. The heat release measured was correlated to the amount of water remaining in the cells at the time of freezing.

2.2.5. Experimental Tissue Freezing Data

Though some data has been collected, it is generally difficult to get freezing data for tissue (Bischof, 2000). For example, pancreatic islets, which

have low cell density and loose connective tissue, have been successfully observed under the microscope during freezing (De Freitas, et al. 1998). Most tissues are more difficult to monitor during freezing, which precludes the use of cryomicroscopy to determine events during cooling. Irimia and Karlsson (2002) did experiments along with modeling on a micropatterned tissue construct to determine the effect of ice nucleation in one cell on adjacent cells. Through the use of microfabrication, the group was able to selectively grow two cells next to each other in order to remove any outside influences, and focus on cell to cell effects which should ideally be similar to effects in natural tissues.

2.3. Thermocouples

Thermocouples were chosen to measure the cell temperature for several reasons. They are a relatively simple instrument and simplicity can lead to easier fabrication and instrumentation. Certain thermocouples can be electrodeposited into recesses, which allows for micro-patterning. In addition, as long as the junction area is small, the response time will be fast and should be more than sufficient to measure the temperature change in the cells. In order to have a better understanding of the methods and characteristics involved with thermocouples in the device, a short introduction to thermocouples, along with some background on micro-thermocouple devices developed in the past is presented.

2.3.1. Introduction

A thermocouple, in its simplest form, consists of two different metals and an EMF measuring device (Figure 2.1). The wires of the two metals meet at two

separate junctions, and a voltage measuring device is placed in series within one of the wires. When there is a temperature difference between the two junctions, there will be a voltage difference within the circuit, measured at the EMF measurement device. If the circuit is closed (no voltage measuring device) then a current will flow instead. For a small change in temperature, there is corresponding small change in voltage, proportional to the Seebeck Coefficient of the metal pair (Eq. (2.1) (ASTM, 1970).

$$dE_s = \alpha_{A,B} dT \quad (2.1)$$

Here, A and B are the two metals of the couple, dE_s is the incremental Seebeck Voltage, dT is the incremental temperature change, and $\alpha_{A,B}$ is the Seebeck coefficient. The Seebeck coefficient depends only on the two metals used in the thermocouple, and the voltage produced is independent of the size or shape of the junctions or of the surrounding circuit, though size can affect junction temperature, and depends solely on the temperature of the two junctions and which conductors are used in the circuit (MacDonald, 1962). Since the voltage measured is based on the difference between the two junction temperatures, one junction is known as the measuring junction, and the other is the reference junction.

There are actually several phenomena that occur when there is a temperature gradient and/or an electric field involved with one or more conducting metals. It is a good idea to have a general understanding of these effects, since they may have an affect on the heat transfer of the system, and they are discussed briefly below.

Figure 2.1. T-type Thermocouple schematic.

Joule heating occurs in a single conductor due to electrical resistivity, and always produces heat. If a current flows through a circuit of two different metals, then heat will be evolved or absorbed at the junction of the metals, depending on the relative Seebeck coefficients and direction of the current through the conductors. This is known as the Peltier effect, and the heat generated does not depend on the size or shape of the junction. (MacDonald, 1962). The Thomson effect is a reversible phenomena, causing heating or cooling, that occurs when there is an electric current flowing through a single conductor where a temperature gradient is also present. The magnitude of this heat generation or absorption is based on the relative direction of current flow and heat flow. When modeling a heat transfer system that includes thermocouples, it is important to determine if Joule heating, and Peltier or Thomson effects will be significant.

2.3.2. Thermocouple Laws

Thermocouple characteristics are governed by three basic laws. These laws are based on experimental results that have been repeatedly confirmed (ASTM, 1970).

The Law of Homogenous Materials: A thermoelectric current cannot be sustained in a circuit of a single homogenous material, however varying the cross section, by the application of heat alone.

The Law of Intermediate Materials: The algebraic sum of the thermo-electromotive forces in a circuit composed of any number of dissimilar materials is zero if all of the circuit is at a uniform temperature.

The law of Successive Intermediate Temperatures: If two dissimilar homogenous metals produce a thermal EMF E_1 when the junctions are at T_1 and T_2 , and an EMF of E_2 when the junctions are at T_2 and T_3 , the emf of junctions at T_1 and T_3 will be $E_1 + E_2$.

(ASTM, 1970)

The first law states that there must be at least two different metals to create an EMF, and any EMF that is measured in a single metal is due to local inhomogeneities, regardless of the level of nonuniformity in the applied temperature. The second law states that another material may be added to the circuit, without changing the properties if its extremities are at the same temperature. In addition, how the junction is formed, as long as it has good thermal and electrical contact does not affect the voltage measurement. The final law states that thermocouples calibrated at one reference temperature can be used at any other reference temperature with a correction factor. In addition, extension wires with the same characteristics as the thermocouple materials can be put into the circuit without changing the EMF.

2.3.3. Reliability and Sources of Error

One aspect that is important to consider in any sensor is how reliable the measurements from that device are. It is important to understand where the error comes from, and how it can be minimized. The section below highlights the areas where error can be accumulated.

Error can come from not having a completely accurate temperature reading on the standard temperature measurement device for the calibration. In addition, a lack of temperature uniformity in the medium used for calibration may cause error, in that the thermocouple is at a different temperature from the standard temperature sensor. There may also be some error from curve fitting between calibration points.

Local (macroscale) inhomogeneities in thermocouple wire composition can cause EMF changes that appear in the voltage measurement. If there is a temperature gradient present through this inhomogeneity, a voltage that will alter the EMF readings between the measuring and reference junction will be generated (ASTM, 1970). This can especially be a concern in electrodeposited thermocouples, since it can be difficult to keep the plating uniform over the entire surface, and therefore, difficult to keep the alloy composition uniform in all areas.

Reference junctions are also sources of error. This error may stem from not accurately measuring the reference junction temperature or from not accurately keeping the reference junction at a standard temperature. Figure 2.2 shows an example of a common thermocouple setup. The reference junctions are found at points 1 and 2 in the figure. This type of circuit commonly contains a

Figure 2.2. Thermocouple schematic with reference junction temperature compensating circuit.

temperature sensitive resistor to compensate for the circuit temperature, therefore keeping the reference junction at a known temperature is unnecessary. In addition, as long as the two junctions and the voltage measuring circuit are at the same temperature (T_2), any conductor may be used in that part of the circuit to accurately measure the temperature at T_1 . If the reference junctions or the circuit are at different temperatures, however, errors can be introduced into the measurement.

When measuring EMF, error can be introduced by the measuring device. Resistance in the thermocouple circuit can influence the sensitivity of the measurement. Reducing the length of wire or increasing the cross sectional area can help to limit this error.

There may be electrical noise from external sources, particularly fluorescent lights, which may induce voltages in the thermocouple wires. This is

especially a concern in the wires before amplification, because the voltages are very small. A remedy is to apply a filter within the circuit to remove stray voltages that occur at a certain frequency.

2.3.4. Transient Temperature Measurement Considerations

In a transient environment, in addition to accurately measuring steady-state temperature, thermocouples must be able to respond quickly to changes in temperature. This means that the thermal capacitance of the junction should be minimized. As a simple approximation, assuming that the junction is at a uniform temperature, one can treat it as a first order lumped system (Goldstein et al., 1998) (Equation 2.2).

$$\rho V c_p \frac{d\theta}{dt} = h A \theta \quad (2.2)$$

Here ρ is the density, V is the volume of the junction, c_p is the specific heat, θ is the difference in temperature between the junction and surrounding fluid, h is the convection coefficient and A is the surface area of the thermocouple. Solving the differential equation, the time constant is shown in Equation 2.3.

$$\tau = \frac{\rho V c_p}{h A} \quad (2.3)$$

The time constant is the amount of time required for the thermocouple to reach 63.2% of the surrounding temperature value, in response to a step change in temperature. The time constant can be used as an approximation to assess how well a certain sized thermocouple junction will respond to the frequency of

temperature change expected. The volume should be minimized and the surface area maximized for the best response time.

2.3.5. EMF Measurement

One of the key elements in the thermocouple circuit is the measurement of the voltage generated. When the reference temperature is known, the voltage measurement will reflect the temperature to be determined. Generally, for making voltage measurements in a thermocouple, a potentiometer is used. The potentiometer works by balancing the voltage from the thermocouple circuit and a standard cell, in order to determine the voltage produced by the thermocouple. The current ideally is zero when the voltage is balanced, so resistance in the wires of the thermocouple circuit should ideally not affect the measurement, but in practice can influence the sensitivity of the balancing galvanometer (ASTM, 1970).

2.3.6. Installation Effects

A consideration that must be investigated in any physical system where data are gathered, is the effect of the observational tools on the quantity being measured. Thermocouples, which have a high thermal conductivity, and are, in this case, in direct contact with the item being measured and can have a significant effect on the sample. In the system being studied, since the sizes are very small, and the thermocouples are comparable in size to the cells, it is possible that they will extract a great deal of heat from the system and change the expected measurement. This problem is further discussed in the modeling section.

2.3.7. Reference Junctions

As stated earlier, a thermocouple gives a voltage measurement based on the difference in temperature between a measuring junction and a reference junction. In order to obtain an accurate reading of the measuring junction temperature, the temperature of the reference junction must also be accurately known. There are three common options for dealing with this situation.

It is possible to use an ice bath to keep the reference junction at 0 °C, and therefore be able to measure the voltage accurately. The key requirement is to have a good mix of ice and water and to ensure that the temperature is uniform; some care must be taken so that the temperature will be very close to 0 °C (ASTM, 1970).

A second option is to use a circuit with a temperature sensitive resistor at the point of the reference junction (Figure 2.2). The circuit compensates for the reference junction temperature. The temperature sensitive resistor must be at the same temperature as the reference junction to accurately give the correct compensation.

Another option is to measure the temperature at the reference junction with another thermocouple, and feed this back into the original circuit to set the compensation. This method can be used when it is not possible to adequately place a temperature sensitive resistor at the point of the reference junction.

2.3.8. Calibration

Thermocouple calibration is necessary in order to accurately correlate a voltage reading on the EMF measurement device to a temperature at the

measuring junction. For standard thermocouple materials, calibration has already been done, and tables or equations are available to convert a voltage reading to a temperature. With this information, any commercial thermocouple can be used off the shelf to give a measurement with some amount of published error off from the standard. In the case of electrodeposited thermocouples, the standard generally cannot be used, as the Seebeck coefficient of electrodeposited metals can vary from the bulk material and because the composition may not be uniform throughout the alloy.

For a macro-scale thermocouple, calibration is done by comparison to another temperature measurement device (ASTM, 1970). The procedure is to maintain the thermocouple at a temperature that is known through another temperature sensing device. The voltage is recorded when the thermocouple is held at several different temperatures, so that the entire range of expected temperature values can be covered. A calibration curve can be fit to the data, so that any point within the range can be measured in practice. In the case of micro-thermocouples, the procedure would be the same, except that care must be taken to ensure that the temperature of the medium used for calibration is kept highly uniform, because of the fact that it may be difficult to accurately mount the temperature sensing standard as close as possible to the micro-thermocouples.

2.3.9. Microthermocouples

Several groups have fabricated micro-thermocouples in the past. Much of the work has focused on microscale temperature measurement of electronics.

The method used is through scanning the surface of these devices with thermocouple sensors placed on the end of an atomic force (AFM) or scanning tunneling microscope (STM) cantilever. Fabrication of these devices is generally through multi-step silicon wafer processing including thin film deposition and chemical etching.

Williams and Wickramasinghe (1986) were the first to put a thermocouple on the tip of an STM. Their objective was to image the surfaces of nonconductive materials, and not specifically for measuring temperature as the end result. The device tip had a size and special resolution of around 100 nm. It was determined that the bulk of the heat transfer from the tip to the surface was through gas conduction, rather than directly from the tip touching the surface. In this case, resolution was based on the mean free path of gas conduction.

More recent micro-temperature sensors have been in the form of AFM tip thermocouples (Shi and Majumdar, 2001), allowing topographic and thermal images of a specimen to be taken at the same time. However, gas conduction was still the dominant means of heat transfer. Luo et al. (1996) used cantilevers with thin film thermocouples and was able to achieve a higher special resolution (below 100 nm), apparently because of liquid film at the contact point. This suggested that the mean free path of gas conduction could be avoided as the limiting factor in temperature measurement, however the results were inconclusive (Shi and Majumdar, 2001).

One of the biggest concerns in microscale thermocouple measurements is the effect of the measuring probe on the environment. The thermocouple tends

to draw heat away from the sample, thus affecting the measurement. Tip design is critical because of this, and the thermal resistance of the cantilever has a direct impact on the resolution and accuracy of the temperature measurements (Shi and Majumdar, 2001) The thermal resistance of the actual cantilever that the thermocouple is attached to should be high, so heat should not flow rapidly down the cantilever away from the sample. In addition to good tip design, Nakabeppu and Suzuki (2002) produced an active thermocouple probe that would attempt to equilibrate the temperature of the tip with the surface, in order to minimize temperature measurement errors through tip to sample conduction. The drawbacks of this method were more complex instrumentation and a slower response time compared to a passive probe with the same geometry, allowing only a 50 Hz sampling rate. Heat flow detection sensitivity in the system was also too small for real temperature measurement.

For the most part, research in microscale thermometry has been limited to individual temperature sensors, though batch fabrication of cantilever microthermocouples has been reported (Shi, et al., 2001). Park and Taya (2004) have reported fabrication of a thin film type-T thermocouple array of 10x10 junctions in a 9 mm x 9 mm area in order to measure the temperature distribution on electronic microchips. Gualous et al. (2001) have tested an Au-Pd thermocouple array of 16 junctions, each with an 8 μ m x 8 μ m surface area and a 140 μ s response time.

3. Thermal Modeling

3.1. Background

Thermal modeling of the micro-thermocouple junctions and their surroundings was done in order to get a better understanding of the local temperature effects from different design factors. This chapter gives a detailed explanation of the prototype device and its operation, discusses the steps used in thermal modeling of the system, and presents and discusses the results.

3.1.1. Objective

The device was to monitor individual cell temperature and cell freezing in a cell tissue culture over a period of time. As a cooling rate is applied to these cells, the temperature drops, and the cells eventually freeze. The freezing of cells releases heat, which can be measured as a transient temperature increase by a thermocouple array spaced on the order of the cell size. Optical methods of determining the time and rate of cell freezing may be inadequate in a tissue culture because it is not always transparent to light. This is meant to be a proof of concept test device to determine the adequacy of this method of temperature acquisition for this application.

3.1.2. Experimental Apparatus

The prototype instrument consisted of a sensing area, instrumentation section, and a cooling stage (Figure 3.1). The sensing area consisted of a thermocouple array with wire traces microfabricated on a single silicon wafer (details on fabrication are given in Chapter 4). The cell culture will be placed at the center of this area, above the thermocouple array, where the individual

Figure 3.1. The experimental setup for the device

measuring junctions are located. The array consisted of 9 thermocouples plus one reference temperature thermocouple (Figure 3.2). The thermocouples were type-T, so one of the leads was copper, and the other lead was constantan (55 % Cu, 45 % Ni). Wire traces transferred the voltage signal to junctions in the instrumentation section. The thermocouples and leads sat on a silicon wafer and in the future, would be embedded in SU-8 photoresist (Microchem, Newton, MA) to create a level surface for the cell culture.

The leads of each thermocouple connected to the instrumentation section through spring-loaded gold fingers. The gold contacts were on a printed circuit (PC) board that contained amplification and reference junction compensation circuitry. The reference junctions for each thermocouple were located at the interface between the gold contacts and the Cu and Cu-Ni wire traces. A separate, off-the-shelf, type-T thermocouple (model 5TC-TT-T-40-36, Omega, Stamford, CT) was used to monitor the temperature at the reference junction,

Figure 3.2. Top view of the thermocouple junction array and leads

and feed that information back for compensation. After the signals were amplified and filtered on the PC board, the analog voltage reading from each thermocouple was sent to a data acquisition card (Model PCI-6229, National Instruments, Austin, TX), to be analyzed on a computer.

The final part of the experimental setup was the cooling stage (Model BCS-196, Linkam®, UK), which used liquid nitrogen to cool a 22 mm diameter circle at the center of the base and a heater to control the cooling rate. The center of the micro-patterned wafer and the thermocouple array were fixed directly above this cooling circle.

3.2. Device Requirements

Ideally, each thermocouple would measure the temperature of an individual cell, without registering any crosstalk from neighboring cells. When a cell freezes immediately next to one thermocouple, an adjacent thermocouple should not also show a significant temperature change. The arrangement of the thermocouples should also be such that it minimizes the space where multiple

thermocouples detect a strong signal from a cell freezing (thermocouples are too close together), but also ensure that they are not so far apart that many cells are not immediately near a thermocouple junction. In addition, the thermocouples in the device should have the smallest possible influence on the thermal characteristics of the environment.

A concept for the shape of the thermocouple junctions was developed and evaluated through modeling. A vertical post layer was inserted between the wiring and thermocouple junctions, to help isolate the cell heat release from the large area of high thermal conductivity wiring that was necessary in the device. A schematic of this arrangement is shown in Figure 3.4, later in the text. The performance of various sizes of posts as well as an arrangement without posts was assessed through thermal modeling.

3.3. Methods and Calculations

3.3.1. Preliminary Models

Two model types were considered before choosing a finite element analysis. Finite difference methods were used first. It was determined that the geometry was too complicated to do a proper model in the time frame allotted. A bond graph analysis was also considered because of the ability to effectively combine multiple energy domains. Thermoelectric, as well as thermal effects can be accounted for using such a model. However, because the currents used in the device were so small, the thermoelectric effects were negligible, and assumed to be unnecessary in accurately solving the problem to the accuracy desired.

3.3.2. Finite Element Modeling

Finite element modeling was determined to be the best way to solve the complex problem of heat transfer through the cell with multiple material types and a complicated geometry. The goal of the modeling was to determine how different factors influenced the thermocouple response. It was not expected to give exact results, but rather to give approximations and trends, in order to aid in the refinement of the design of the instrument. The procedure for modeling the device using ANSYS finite element software (Version 9.0, Canonsburg, PA) is outlined in the following sections. The modeled system consisted of an SU-8 base with embedded thermocouples, a single cell, and surrounding tissue culture (Figure 3.3). A cooling rate was applied to the system to simulate the action of the cooling stage, and a heat generation rate was applied at the cell to simulate cell freezing. The temperature response at the thermocouple junctions was observed as the parameters were varied.

3.3.2.1. Assumptions

3.3.2.1.1. Thermoelectric Effects

One of the concerns in modeling the system was the significance of thermoelectric Peltier, Joule, and Thomson effects on the heat transfer characteristics. Each of these effects is based on the amount of current flowing through the conductor. In an ideal case, the Seebeck coefficient would be measured with an open circuit, and none of the other thermoelectric effects would occur. The EMF measuring device actually used in the circuit would make current close to zero during measurement. For example, the magnitude of the

Figure 3.3. Finite element modeling setup. (a) Entire model view. (b) Detailed view of cell and thermocouple junctions.

voltage generated by a type-T thermocouple with a 2 °C temperature change is -76 μV (ASTM, 1970). If the circuit resistance, including the voltage measurement device, is 1 M Ω , the current would be $\sim 7 \times 10^{-11}$ A. Since the magnitudes of these effects are all based on the magnitude of the current, the contributions will be negligible, and should not significantly influence heat transfer in the system.

3.3.2.1.2. Latent Heat Release of Cells

A cell, though comprised mostly of water, tends to freeze at temperatures lower than the expected freezing point of water. The energy released from the latent heat of fusion of ice when the cell freezes changes the local temperature. Cell freezing in the finite element model was treated as a material property change from water to ice, accompanied by volumetric heat generation. The calculations for determining the duration and heat release are detailed in section 3.3.2.7.

3.3.2.2. Geometry

3.3.2.3. Cell Size and Thermocouple Spacing

The cells used in the design of the device were Neonatal Human Dermal Fibroblast (NHDF) cells, which have a mean diameter of 30 μm . In order to measure the temperature in the neighborhood of a single cell, the center to center spacing of the thermocouples needed to be comparable. Since the spacing was small, one of the concerns was that modeling might show that a cell freezing near one thermocouple registered strongly at another thermocouple as well. This would cause a problem in terms of recognizing whether a single cell froze, or if multiple cells froze because the temperature jump might be read on multiple thermocouples. Therefore, one modeling goal was to establish if this was a problem, and if it could be minimized, through some sort of insulation or by increasing the spacing between thermocouples, if necessary. Thermocouple spacings, center to center, of 45 μm , 50 μm and 55 μm were modeled to determine any trends. The smallest possible spacing with the current fabrication techniques is 45 μm , and the other two spacings were chosen arbitrarily.

3.3.2.2.2. Model Simplification

One of the concerns in modeling the system was that the entire microsystem, including the thermocouple array and leads, was very large (3 cm diameter) compared to the smallest structural entity fabricated in the device (3 μm diameter). In order to properly model the system with finite elements without requiring a prohibitive number of elements, smaller boundaries were chosen for the system.

The boundary was chosen large enough so that the size did not influence the results at a single device, but small enough that the number of elements needed to compute a solution did not become problematic. Figure 3.3, presented earlier, shows the selected boundary area, a size of 500 μm x 250 μm x 300 μm . The size of the area chosen was tested by expanding the boundaries and running the same simulation case again to determine the magnitude of changes in the results. A 40 % increase in size created a 0.007 % change in temperature at the thermocouple junction.

Another method used to simplify the system was to limit the number of thermocouples to three, instead of the nine that are present in the actual the 3 x 3 array on the device. This was done because of difficulties in meshing the full array. The justification for using only 3 thermocouples was provided by modeling geometries of, one, two and three thermocouples, and comparing the difference in results. This data are presented in section 3.4.5.3 later in the chapter.

3.3.2.2.3. Effect of Thermocouples on the System

In designing the arrangement of the device, alternate thermocouple geometries were modeled. The main concern in introducing thermocouples into a cellular system was the effect on the environment being measured. Since the thermocouples had high thermal conductivity compared to the surrounding medium, they would tend to rapidly conduct heat away from the cell. When a cell froze, a thermocouple might not register strongly enough and the voltage reading might be too small to adequately distinguish from noise, keeping in mind that the sensitivity of a type-T thermocouple is only 38 $\mu\text{V}/^\circ\text{C}$. Figure 3.4 shows two

proposed thermocouple junction designs. Both designs have a wiring layer and junction layer, with one of the designs employing an intermediate “post” layer. The reasoning behind the two separate designs was based on the idea that the wiring layer would significantly influence the system temperature due to the relatively large volume of wires. An intermediate post layer might reduce the effect of the wiring, and provide some thermal insulation between the cell and the high conductivity wiring layer. Part of the modeling goal was to determine the magnitude of the effect an intermediate post layer would have, since it would require more steps to fabricate than the design without the intermediate layer.

A second design goal was to have the thermocouples as isolated as possible, from each other, minimizing interference between adjacent thermocouples. Modeling of the system would help answer the question of how much isolation was required. It would be possible to determine if additional insulation was needed between adjacent thermocouples. The two design

Figure 3.4. Possible thermocouple junction geometries. (a) Junction arrangement with an intermediate post layer to aid in isolation of junction from wiring layer. (b) Junction arrangement without a post layer.

possibilities, with and without intermediate posts, were also tested for the amount of interference between thermocouples.

3.3.2.2.4. Tolerance and Fabrication Limits

Modeling can help determine what thermocouple dimensions are best, but there is also a size limit based on fabrication capabilities. These fabrication issues are covered in more detail in Chapter 4 on fabrication, but will be highlighted here briefly for clarity. The sizes tested in the thermal modeling were based on research and experiments done to determine what structure dimensions could be readily fabricated. The height of the leads was limited by the ability to plate constantan uniformly in a recess and the thickness of the positive resist after spin coating. Second, there was a limitation on how small the thermocouple post diameter could be made due to UV mask fabrication and exposing and developing resist. Third, the junction area was limited by the tolerances involved in mask alignment.

3.3.2.3. Boundary Conditions

Figure 3.5 displays the boundary conditions. The four vertical wall conditions were treated as insulators, to represent periodic boundary conditions in those directions. This was a simplification, because the actual heat flux leaving the walls was unknown, but the boundary size was large enough that insulation on the walls should not have affected the results at the junctions. The top surface was treated as convection to air, with an average convection coefficient of 10 W/m^2 (Incropera and Dewitt, 1996). The bottom boundary was a

Figure 3.5. Boundary conditions for the thermal model.

uniform heat flux to represent the cooling of the stage. The calculations for the flux are presented in section 3.3.2.6.

3.3.2.4. Material Properties

Several materials were used in the modeling of the system (Table 3.1). The cell culture, which includes cells as well as extracellular fluid, was treated as water for this analysis. In an actual experiment, it would be a mixture of water and ice, as the extracellular fluid and some of the cells would be frozen, while

Table 3.1. Material properties used in finite element model

Model Section	Material Used	Density, ρ (kg/m ³)			Specific Heat, c (kJ/kg-K)			Thermal Conductivity, k (W/m-K)			Data Source
		100K	200K	273K	100K	100K	273K	100K	100K	273K	
Cell before freezing	Water	999	999	999	4200	4200	4200	0.6	0.6	0.6	Kandra & Devireddy, 2004
Cell after freezing	Ice	921	921	921	854	1570	2093	4.55	3.09	2.24	
Surrounding cells and cell medium	Water	999	999	999	4200	4200	4200	0.6	0.6	0.6	
Device base	SU-8/PMMA	1190	1190	1990	1400	1400	1400	0.17	0.17	0.17	Goodfellow, Inc.
Copper lead	Copper	8933	8933	8933	252	356	377	482	413	404	Incropera & DeWitt
Constantan lead	Constantan	8920	8920	8920	237	362	378	17.0	19.0	21.9	

some of the cells would be unfrozen. The model was also run with the extracellular fluid treated entirely as ice, and the results are given in section 3.4.5.3. To facilitate meshing, the device base was treated as entirely SU-8, rather than SU-8 surrounding the thermocouples on the sides with the silicon wafer base below. Since silicon is more thermally conductive than SU-8, actual results with a silicon wafer base should show a higher amount of heat transfer away from the cell. The original device was intended for fabrication in PMMA and this is how the modeling was done, however SU-8 was used in the final design. SU-8 properties approximate PMMA very closely (Table 3.2) and the PMMA properties were used in the analysis.

3.3.2.5. Meshing

Meshing was done using tetrahedral elements since the geometry was too complicated for quadrilateral elements. In an ideal situation, the volumes would be meshed with the same size elements, but because the smallest feature size is 3 μm , it would mean that all of the elements in the model would need to be smaller than 3 μm , which was not feasible with the software available. The University Advanced version of ANSYS allows only 128,000 elements. Different sizes were used for the different volumes in the model, to allow the features to

Table 3.2. Thermal property comparison of SU-8 and PMMA. SU-8 data from Cordero, et al. 2004; PMMA data from Goodfellow, Inc.

Material	Conductivity (W/mK)	Density (kg/m ³)	Specific heat (J/jgK)
SU-8	0.2	1120	1400
PMMA	0.17	1190	1400

mesh without having a prohibitive number of elements (Table 3.3). The sizes listed in the table were input into ANSYS, but were not necessarily those used in each element of a model component. Since the volumes were complex and a free mesh was used, the sizes were adjusted within the software to fit the model geometry. To test the effect of mesh size on the modeling results, mesh refinement was performed, and the details are explained in section 3.4.5.2 of this chapter.

3.3.2.6. Cooling Rate

It was necessary to determine the flux through the lower boundary of the system that would achieve the proper cooling rate at the cell. For modeling this system, the two extremes of cooling that would be tested with the actual device were chosen. The smallest cooling rate expected was 5 °C/min, and the largest cooling rate was 500 °C/min. The model was run with both of these cooling rates at the cell. Since the cooling rate was known, but the heat flux through the bottom required to make this rate at the cell was unknown, some test cases were used to determine the proper flux for both cooling rates. The test system used

Table 3.3. Mesh sizes used in the thermal model.

Model component	Element edge size (μm)
Junctions	2.5
Posts	2.5
Wires	2.5
Cell	2.5
Surrounding cell medium	50
SU – 8 (near thermocouples)	8
SU-8 (device base)	50

was simply an SU-8 base with cell medium and a cell on the surface (Figure 3.6). No thermocouples were included in this model and cell freezing was not simulated. For 5 °C/min, the flux was -350 W/m^2 , and for 500 °C/min, the flux was -5680 W/m^2 .

3.3.2.7. Cell Freezing Time

Once the proper cooling rate was applied to a control case, the SU-8 base without thermocouples, the next step was to determine the proper parameters for modeling the freezing of the cell. Two situations were considered: a cooling rate of 500 °C/min with ice nucleation within the cell at -20 °C , and a cooling rate of 5 °C/min with ice nucleation within the cell at -5 °C . Cell freezing was modeled as a volumetric heat generation rate applied when the cell reached the appropriate threshold of temperature, either -5 °C or -20 °C .

Figure 3.6. The system used for the control case thermal model.

In order to know the proper heat generation rate to apply, some preliminary calculations were performed. The amount of energy released when water freezes was known, since this is equal to the latent heat of fusion of water, 308,500 kJ/kg at -5 °C and 242,400 kJ/kg at -20 °C (Hobbs, 1975). The length of time of the release of this energy, however, and the corresponding heat generation rate, was unknown. Kandra and Devireddy (2004) determined what the temperature rise at a cell should be when it freezes with different applied cooling rates. They found a 1.89 °C rise for a cell freezing at -5 °C with 5 °C/min cooling, and a 0.49 °C rise for a cell freezing at -20 °C with 500 °C/min cooling. Using these values as goals, it was possible to estimate the heat generation rate required for the finite element model through iteration. The heat generation rate was related to the time of freezing by Equation (3.1).

$$\dot{q}_{cell} = \rho_{water} \frac{l_{water}}{t} \quad (3.1)$$

Here, $\dot{q}_{cell}$ is the volumetric heat generation rate supplied by the cell, ρ_{water} is the density of water, l_{water} is the latent heat of fusion for water at the temperature of freezing and t is the time length of freezing. It was assumed that the heat generation rate was constant during the time of heat release of the cell. An arbitrary heat generation rate was chosen for the first iteration, and a corresponding duration of freezing was calculated from Eq. (3.1). A control simulation was then run, using the same system (a system without thermocouples) as the one used for cooling rate testing. The temperature rise at the cell center was recorded, and the heat generation rate and freezing time were altered; and the simulation repeated until the temperature rise matched the

results from Kandra and Devireddy (2004). The results from this study for 5 °C/min were a rate of 10,255 pW/μm³ for 0.015 seconds, and for 500 °C/min were a rate of 5,350 pW/μm³ for 0.023 seconds.

3.3.2.8. Thermocouples

With the heat generated at the time of cell freezing known, the thermocouples were added to the system to observe the effect. Several different thermocouple sizes, presented in Figure 3.7, were tested with the model. Four different vertical post cases were tested, along with a fifth case, without vertical posts. The sizes used in the model were based on what was feasible for

Figure 3.7. Thermocouple dimensions used in the thermal model. Four variations of designs with posts were used, as well as one design without posts.

manufacture, although some differences do exist between the sizes used in the model and the actual sizes used in the device. In the actual device, the junction and base sizes had to be altered to solve tolerance issues, but in the model, only the post size was varied in order to isolate the effect on the system.

3.4. Results

3.4.1. Thermocouple Effects on the System

Simulations were run with the five different geometries outlined in section 3.3.2.8. The results are presented in Figure 3.8 for 5 °C/min and 500 °C/min cooling rates, respectively. Temperature rise is shown as a function of time. The control case refers to the temperature at the center of the cell when thermocouples were not present in the system. The remaining variables (cases 1 through 5) show the temperature at the junction of the thermocouple directly below the freezing cell when three thermocouples were included in the model. The freezing (heat generation) was introduced into the model at 8 seconds for the 5 °C/min case and at 5.4 seconds for the 500 °C /min case. The data were offset so that the temperature rise for each case begins at -5 °C or -20 °C, to facilitate visual comparison. In the actual data, there were some small variations in the nucleation temperature for each case.

The thermocouple geometry that registered a temperature rise as close as possible to the control case was deemed best. The results showed that there was a significant change in temperature when the thermocouples were in the system, as opposed to the control case, but there was still a measurable temperature increase. The temperature difference between the various

Figure 3.8. (a)Temperature rise as a result of cell freezing for a 5 °C per minute cooling rate with a -20 °C nucleation temperature. (b)Temperature rise as a result of cell freezing for a 500 °C per minute cooling rate with a -5 °C nucleation temperature.

geometries was not large, but the case without vertical posts did not register the lowest temperature jump. The posts that were 5 μm in diameter showed a larger temperature drop, with more heat drawn away from the cell, than either the case without posts or the case with 3 μm diameter posts. This indicates that the greater diameter of the 5 μm posts offset the insulation of the SU-8 between the cell and the wiring layer, and the overall conductivity through the posts was greater than the conductivity through the wiring layer. The posts are meant to isolate the cell from the wiring, but at 5 μm , they are much larger than the individual wires. This is significant because a large portion of the heat leaves the cell from the wires in contact with the it.

The thinner, 3 μm posts did provide some benefit as compared to a system without an intermediate post layer. The best case was achieved with the tallest, thinnest posts, which is limited by fabrication capabilities. The cross over in performance between posts and no posts indicates that there is a point where the diameter of the post is too large to increase the overall thermal insulation of the cell. More modeling could help determine get a better idea of this value, and also how much of the relative thermal resistance is from the posts and the wiring layer.

3.4.2. Thermocouple Isolation

The amount of interference between adjacent thermocouples was also examined using the thermal model. Figure 3.9 displays the results of the modeling for thermocouple center to center spacing of 50 μm . When a cell froze above a thermocouple, there was no significant temperature jump registered at

Figure 3.9. (a) Comparison of temperature readings at the thermocouple directly below the freezing cell and the adjacent thermocouple, for a 500 °C per minute cooling rate with a -20 °C ice nucleation temperature. (b) Comparison of temperature readings at the thermocouple directly below the freezing cell and the adjacent thermocouple, for a 5 °C per minute cooling rate with a -5 °C ice nucleation temperature.

the adjacent thermocouples, regardless of the thermocouple height and diameter. This implied that a large amount of the heat release from the cell traveled through the thermocouple directly below it, drawing the heat away and reducing the amount of heat conducted to adjacent thermocouple locations. There was not a clear difference between any of the geometries, and therefore there was not one size that was a clearly superior to the others, in terms of isolation. The effect of the amount of spacing between thermocouples was also tested, for different thermocouple geometries, with a 5 °C per minute cooling rate and a -5 °C nucleation temperature. Figure 3.10 displays results for

Figure 3.10. Plot of maximum adjacent thermocouple temperature rise as a function of thermocouple center to center spacing. Results shown for a 5 °C per minute cooling rate with a -5 °C ice nucleation temperature.

thermocouple center to center spacings of 45 μm , 50 μm , and 55 μm . The temperature rise plotted refers to the maximum temperature rise registered at an adjacent thermocouple when the cell froze above the center thermocouple. The geometry of the thermocouples chosen did not have a strong effect on the adjacent temperature registered, but there was some effect due to the center to center distance, with a larger separation leading to a smaller response at the adjacent thermocouple. For case 1 (20x3), the adjacent temperature reading decreased by 7 % between 45 μm and 50 μm spacing, and by 12 % between 50 μm and 55 μm spacing, with similar results for the other geometries. Although one of the goals was to create a thermocouple array where interference between thermocouples was minimized, implying larger spacing, it was also important to consider the size of the cells, so that individual cells were addressed. As the spacing is increased, there is an increasing chance for more cells to be in between thermocouples, and not near a particular junction.

3.4.3. Cell Placement and Thermocouple Spacing Effects

The results presented thus far have assumed that a cell freezes directly above a thermocouple junction. In an actual device, the cells will be arbitrarily distributed over the surface of the thermocouple array, and not every cell would be immediately adjacent to a thermocouple. Simulations were run with varying cell positions and three different lengths of thermocouple center to center spacing. The results are presented in Figure 3.11 and Figure 3.12. The temperature rise at the center thermocouple and at the adjacent thermocouple as functions of the cell placement between the two thermocouples are presented.

Figure 3.11. Thermocouple temperature increase based on cell position. Temperature increase at the center and adjacent thermocouple is plotted versus nondimensionalized cell position between the two thermocouples. (a) Plot for Case 1 (20x3) geometry. (b) Plot for Case 3 (20x5) geometry.

Figure 3.12. (continued from Figure 3.11) Plot for Case 5 (No Leads) geometry.

As the cell moved closer to the adjacent thermocouple, naturally, the center thermocouple temperature rise decreased and the adjacent thermocouple temperature rise increased. Each plot compares three different spacings (45 μm , 50 μm and 55 μm) for a single thermocouple geometry, to emphasize the effect of the spacing on the temperature rise. Generally, curves with gradual slopes near the junctions and steeper slopes near the center would be optimal, there is a smaller area where the center and adjacent thermocouples show similar temperatures. In this case, 45 μm spacing provided the best results. As for thermocouple geometry, the geometry without leads provided the lowest (least favorable) slope near the center, and therefore poorest results. The results from Case 1 and Case 3 were comparable.

3.4.5. Result Verification

In order to have confidence in the methods and parameters used, as well as in the assumptions taken, several methods of numerical testing were performed. Actual experimental testing is the only thing that can give complete confidence in results, but it is helpful to have a preliminary check of the data when no experimental data is yet available.

3.4.5.2. Mesh and Time Step Refinement

Mesh sizes were determined based on trial and error using a free mesh, with the main limitation being the element number limit (128,000) for the University Advanced license of ANSYS (Version 9.0, ANSYS, Inc., Canonsburg, PA). Ideally, the entire volume within the boundaries of the model could be meshed with a uniform mesh size, and the results could be tested with successively smaller mesh sizes, with each size being half the size of the larger one. The results would be compared in order to ensure that the size of the mesh was not greatly affecting the results. However, because of the limitation on the number of elements, different volumes in the model were meshed with different element sizes. In addition, mesh refinement could not be performed over the entire model, but was limited to the volume of the freezing cell.

In order to test the influence of mesh size on the system, three different mesh sizes were considered: coarse, medium and fine. The side length of the medium element was chosen to be half of the coarse element size, and the side length of the fine element was chosen to be half of the medium size. For this model, the coarse size was 10 μm , medium was 5 μm and fine was 2.5 μm .

Two checks were performed on the results, a check for *convergence*, and a check for a *converged* result. Convergence means that the difference in results between successive mesh sizes is decreasing. Equation (3.2) for checking convergence is shown below.

$$\left| T_c^{\max} - T_m^{\max} \right| > \left| T_m^{\max} - T_f^{\max} \right| \quad (3.2)$$

Here, $T_c^{\max}$, $T_m^{\max}$ and $T_f^{\max}$ are the temperatures obtained using the coarse, medium and fine meshes, respectively. If the inequality in Eq. (3.2) is satisfied, it indicates that the solution is converging.

A converged result means that the error obtained between the medium and fine mesh was below a desired threshold error level. Equation (3.3) for testing a converged result is shown below.

$$\left| T_m^{\max} - T_f^{\max} \right| < e_s \left| T_f^{\max} \right| \quad (3.3)$$

Here, e_s indicates the error level sought, which is subjective, but a general rule of thumb is that below 0.01 is excellent, below 0.02 is good and below 0.05 is satisfactory (Sinclair, 2005). This analysis was performed on case 2 (50x3) geometry with three thermocouples present and a cooling rate of 5°C/min and 500°C/min, with the temperature taken as the maximum measured temperature increase at the center thermocouple junction. The results are summarized in Table 3.4. The testing indicates that for all cases, the results were converging, and the error level achieved was satisfactory (below 0.05).

In addition to mesh refinement, the length of time for each time step was also tested. A single time step is an instance in the transient model where

calculations are done based on the current boundary and system conditions and the previous state temperature distribution. It was important to determine if the number of time steps chosen influenced the results achieved. The analysis for the time steps was performed in the same manner as the mesh testing analysis. The segment of the thermal analysis chosen for testing was the heat generation phase of the cell, with a time of 0.015 seconds for a 5 °C/min cooling rate and 0.02257 seconds for a 500 °C/min cooling rate. The conditions were 2 steps for coarse, 4 for medium and 8 for fine within the heat generation time span. The temperature used in the analysis was the maximum measured temperature rise at the center thermocouple junction. The results (Table 3.4) gave better converged values than the mesh size refinement, and showed converged values of below 0.02.

3.4.5.3. Geometry and Material Variation

Additional tests were performed with the model to gain confidence in the results. One of the issues in modeling the system was that the number of available elements would not allow a full model of nine thermocouples. Model

Table 3.4. Thermal model convergence testing data

Variable	Mesh Refinement		Time Step Refinement	
	5°C/min	500°C/min	5°C/min	500°C/min
$T_c^{\max}$	1.2013 K	0.5465 K	1.2264 K	0.5786 K
$T_m^{\max}$	1.2464 K	0.5864 K	1.2636 K	0.6003 K
$T_f^{\max}$	1.2814 K	0.6110 K	1.2814 K	0.6110 K
$ T_c^{\max} - T_m^{\max} $	0.0451 K	0.0399 K	0.0372 K	0.0217 K
$ T_m^{\max} - T_f^{\max} $	0.0350 K	0.0246 K	0.0178 K	0.0107 K
e_s	0.0273	0.0403	0.0139	0.0175

results are presented with three thermocouples, but results were also obtained for geometries of one and two thermocouples. These results are presented in Figure 3.13. The data are given for all five of the cases and for 5 °C/min and 500 °C/min cooling rates. There is little variation between 1, 2 and 3 thermocouples. The results indicate that most of the heat transfer from the cell is from the center thermocouple beneath the cell, and adjacent thermocouples do not significantly influence the center thermocouple temperature. The results obtained from the three thermocouple system should give comparable results to that of a nine thermocouple system.

A final test was performed on the model assuming that the entire top layer of cells and solution to be ice. Everything else in the model was unchanged, but the material used for the cells and cell medium were switched to ice. The test was run for Case 1 (20x3) at a 5 °C/min cooling rate. The temperature increased by 0.73 °C, as opposed to an increase of 1.29 °C when the model was run with water. This indicates that there was a significant difference with the cell culture as ice and the cell culture as water. This is likely due to the difference in thermal conductivity of the two materials. However the actual temperature increase would be somewhere in between the two temperatures, because the whole cell culture is generally a mixture of both ice and water. Additional modeling with ice may be necessary in the future.

3.5. Discussion

Thermal modeling of the instrument helped to give more information on three main points: how much the thermocouple geometries affected the

Figure 3.13. Comparison of thermocouple temperature increase with one, two and three thermocouple junctions used in the model system. (a) 5 °C per minute cooling rate with a -5 °C ice nucleation temperature (b) 500 °C per minute cooling rate with a -20 °C ice temperature

temperature reading of the control case, how much the thermocouple geometries affected adjacent thermocouple response, and how much the spacing of the thermocouples affected the temperature measured at junctions. This section will attempt to analyze the information that was gathered.

With smaller thermocouples, a quicker response time is expected, and less heat drawn away from the cell, leading to a measurement system which is closer to an undisturbed system. In measuring how much the thermocouples affected the control case, it was shown that there was not a significant difference between the geometries tested. The most favorable geometry, case 2, 50x3, had a 31 % drop in temperature from the control case, and the least favorable geometry, case 4, 50x5, decreased 41 %. However, thinner and taller posts between the junction and wiring layers improved the simulated response temperature. If fabrication limitations were not an issue, increasingly thin and tall thermocouple posts would lead to better performance. The actual fabrication limit is unknown, as 20 μm tall by 3 μm diameter posts were the smallest sizes attempted, though perhaps nanowires may be an option.

In terms of thermocouple geometry affecting adjacent thermocouple response, there was negligible difference. Each of the geometries had an almost identical adjacent thermocouple response, which was very small, compared to the center thermocouple measurement (around 16% of the control case temperature rise). Since the data are similar for all cases, the thermocouple arrangement that was the most reliable to fabricate would be best. This is Case 5, without leads, because fewer fabrication steps are required.

In terms of determining the effect of thermocouple spacing, two tests were performed. One test was to observe adjacent thermocouple response with a cell freezing directly above the center thermocouple for 45 μm , 50 μm and 55 μm spacing. The best results, with the smallest adjacent temperature rise, were shown at 55 μm spacing, with around a 23 % decrease in adjacent temperature rise compared to the 45 μm case. However, this was not the only factor influencing the decision on thermocouple spacing. A second test was performed, comparing the spacing of the thermocouples when a cell froze at different points between the center and adjacent thermocouple. It was beneficial for cells to be in close contact with the thermocouple junctions, to minimize temperature rise at adjacent junctions. In this case, a smaller thermocouple spacing arrangement of 45 μm was best, which gave a better chance for cells to be near a thermocouple junction.

The modeling results can only give suggestions as to what geometry was best, but it was important to also determine what is most feasible to fabricate, before making a final decision. Chapter 4 explains in detail the fabrication of the device.

4. Fabrication

Before proceeding to make the device, it was important to determine some of the limitations of the fabrication process and optimize the procedures. The following chapter gives an overview of the fabrication process, details the analysis and experiments performed to aid in fabrication, and then explains the final device fabrication process in detail.

4.1. Background

Several groups have fabricated microthermocouples, though previous work has been using thin films. The fabrication methods were through patterning either sputtered or electron beam deposited metals on silicon substrates. A micro thermocouple array with an intermediate post layer through electrodeposition has not been fabricated previously.

For fabricating thin film thermocouples, the methods are generally similar. Shi and Majumdar (2001) used a multi-step sputtering process on a silicon wafer that used buffered hydrofluoric acid etching of the silicon wafer to create cantilever tips. The two metals for the thermocouple were sputtered, with an electrically insulating layer in between, to create the thermocouple. Park and Taya (2004) fabricated a type-T thermocouple array by alternately depositing copper and constantan layers on an AlN coated silicon wafer. The AlN acted as an electrical insulator and thermal conductor between the thermocouples and silicon wafer substrate. Gualous, et al. (2001) also thin films to create an array of Au-Pd microthermocouples.

4.2. Fabrication Outline

The fabrication of this device was done through a multi-step UV lithography-based microfabrication technique. Figure 4.1 gives an overview of the steps in the microfabrication process.

Fabrication was done on two types of silicon wafer substrates, to determine if both would have suitable electrical resistivity to isolate individual wires on the wiring layer. One wafer was of high resistivity (63-77 $\Omega\text{-cm}$), and the other was a low resistivity wafer (1-5 $\Omega\text{-cm}$) with a 4.5 μm SiO_2 layer on the surface. The first step was to electron beam (e-beam) evaporate a 0.01 μm titanium adhesion layer and a 0.05 μm copper plating base to facilitate electrodeposition in future steps. Then a 2 μm layer of S1813 resist (Rohm and

Figure 4.1. Fabrication outline. (1) Silicon wafer base. (2) E-beam deposit titanium and copper. (3) Spin S1813 resist, expose and deposit copper wiring layer. (4) Spin S1813 resist. (5) Expose and deposit constantan wiring layer. (6) Remove resist. (7) Spin AZ 4620 resist. (8) Expose and deposit copper post layer. (9) Spin S1813 resist. (10) Expose and deposit constantan post layer. (11) Expose and deposit copper junction layer. (12) Remove resist. (13) Etch copper and titanium base. (14) Cast SU-8. (15) Develop down to junction layer.

Haas, Philadelphia, PA) was spin-coated and baked on the wafer for the first wiring layer. A UV exposure was performed, the resist was developed, and copper was deposited into the micropatterned wiring layer recess. A second layer of S1813 resist was spun and baked on the wafer to prevent future electrodeposition on the already deposited copper layer. An aligned exposure was performed for the second wiring layer, and constantan was electrodeposited into this set of recesses. The resist was removed completely, and an 18 μm layer of AZ 4620 (AZ Electronic Materials, Somerville, NJ) resist was spin-coated and baked over the wiring layer. An aligned exposure was made and the copper posts were electrodeposited. A thin layer of S1813 resist was spin-coated on top to prevent future electrodeposition on the already deposited copper posts. The constantan post layer was then aligned, exposed, and electroplated. A final aligned exposure was made for the junction layer, and copper was plated in the exposed pattern. The remaining resist was completely removed, and the copper plating base and titanium adhesion layer were etched away. Although this step was skipped because of time constraints, SU-8 10 (Microchem, Newton, MA) would be cast and developed to provide a surface within which the thermocouples would lie.

4.3. Resist Parameter Optimization

The UV lithography process involves the use of UV sensitive resist and a photomask. The mask is made of clear soda lime glass or quartz with a chrome pattern in the shape of the structures. A resist is applied to a substrate, generally through spinning or casting, and is exposed to UV light that passes only through

transparent regions on the mask. If the resist is a positive resist, the parts that are exposed to UV light will become more soluble in a developer. When the substrate and resist are placed in the developer, these exposed areas will be dissolved, revealing the base below and leaving the unexposed portions intact. If the resist is a negative resist, the UV exposed areas will crosslink, and become less soluble in the developing solution. When the substrate and resist are placed in the developing solution, the unexposed areas will dissolve.

One decision made for the fabrication process was to use positive resists. Although, generally, negative resists are more durable, less sensitive to overdeveloping, and some are designed for greater thicknesses, a positive resist was required for this application because of the sequence of the fabrication process (Madou, 2002). Two successive exposures were required in the same resist layer to allow electroplating of two different metals on the same layer. Once a negative resist is exposed, the cross linked area is no longer sensitive to UV light, rendering a second exposure on already exposed areas ineffective.

The fabrication of the device was very close to the capability limits of the facilities available. Proper alignment was critical, and over-exposure or over-developing of the resist was potentially a problem. Since the two metal structures were very close together ($< 3 \mu\text{m}$), it was important to optimize the different steps in the microfabrication process (Figure 4.2) to ensure there was no unwanted electrical contact between wires. The factors with the most influence on the structures were exposure dose, development time, and strength of the vacuum contact during exposure. If the exposure is too short, insufficient

Figure 4.2. Optimization of fabrication parameters for the wiring layer. (a) The original mask. (b) Exposure and development have not been optimized (structures are much wider than the mask). (c) Optimized exposure and development.

photon energy reaches the bottom part of the resist, so solubility is not sufficiently increased. Even with a long developing time, the plating base may not be exposed, and the subsequent metal electrodeposition step would not be possible. If the exposure is too long, the areas around features will experience sufficient photon energy that more resist will be dissolved during the developing step, leaving a pattern larger than expected. Ideally it is best to modify the exposure dose so that it is as low as possible, and use a weak developer so that small changes in developing time do not greatly affect the size of the structure. If the vacuum contact was not sufficient, structures would be larger than expected. Diffraction would occur if there was not good contact between the sample and the mask.

4.4. Tolerance Analysis

A tolerance analysis is important for the design of almost any device, but it is especially critical for this work because the dimensions in the microfabrication design are near the level of uncertainty in alignment. The sizes of the features on each layer had to be kept small in order to maintain the spacing required for addressing individual cells. However, if the dimensions of features in a layer were designed too small, and the alignment error was large, there could be

places where the electrical connection is lost, or places where two different metal leads touch and short out. A tolerance analysis was performed to help determine the smallest size components that could be used in each successive layer.

4.4.1. Background

A one dimensional tolerance analysis based on Drake (1999) was performed. Using this method, the first step was to identify performance requirements for the device in terms of dimensions. Based on these requirements, a dimension (known as a gap) in the device or assembly is selected that needs to be kept above or below a certain value. A tolerance loop is created, which starts from one point on the assembly and linearly follows all relevant dimensions through the system, including the gap, returning to the original point. Using a worst case tolerance analysis, going through the entire loop, all of the tolerances for each individual dimension are summed together, to give the total tolerance for the gap. The gap distance minus the total tolerance of the system should be larger than the minimum acceptable value for the gap, and the gap distance plus the total tolerance should be smaller than the maximum accepted value for the gap. If it is outside of the requirements, then lengths or tolerances of features must be changed somewhere in the loop until the appropriate sized gap, with appropriate tolerances is achieved.

4.4.2. Description of Analysis

A separate one-dimensional analysis was performed for each layer to isolate the tolerances for that layer. Certain additional critical distances were identified and analyzed to ensure that the fabrication would fit within the required

limits. Two separate sets of dimensions and tolerances were analyzed; one set had larger post sizes and alignment tolerances to ensure the highest chance of success in fabrication.

Figure 4.3 shows the tolerance loop for the first layer of the device. In the figure, A1 is the center to center distance of the alignment mark to the pad of the copper wiring layer. For the analysis, the length is arbitrary, and was assumed to have a tolerance of zero. The reasoning for this was that there are tolerances included later for the dimensions of both the alignment mark and the pad, so, including center to center error would be redundant and lead to an overestimation of the total tolerance necessary. The distance from the center of the pad to the pad edge is B1. The tolerance here was $\pm 0.4 \mu\text{m}$, which was the tolerance given by the mask manufacturer (Advance Reproductions, North Andover, MA). One assumption made in this loop was that the fabricated

Figure 4.3. First layer (Copper wiring) tolerance loop.

structures would be the same size as the UV mask pattern. It was believed that through optimization of exposure time and developing, feature sizes could be kept very close to the mask sizes. For example, testing showed that the post sizes could be made as much as $0.5\text{ }\mu\text{m}$ smaller at the base than the design size (Figure 4.8). Therefore, tolerances given on structures in the design are based solely on mask feature tolerances. The distance between the edge of the copper pad, and the absolute centerline between the constantan and copper pads is C1. This gap was analyzed to determine if it was the correct size, based on the accumulated tolerance of the system. The distance from the center point to the center of the alignment mark is D1. There was no error included on this line. The total tolerance from this first level loop was $\pm 0.4\text{ }\mu\text{m}$ (from B1 only), and therefore the gap tolerance was $\pm 0.4\text{ }\mu\text{m}$ as well. The table with the figure shows dimensions and tolerances for both a thermocouple junction arrangement with $3\text{ }\mu\text{m}$ and $5\text{ }\mu\text{m}$ diameter posts.

Figure 4.4 shows the second layer of the device. Here, the situation was more complicated, with alignment now required between the first and second layers. The distance from the center of the second layer alignment mark on the mask to the center of the pad on the mask is A2. The distance from the center of the pad to the edge of the pad, both on the mask is B2 ($\pm 0.4\text{ }\mu\text{m}$). The distance from the edge of the pad on the mask, to the centerline is C2. This is the gap dimension, for which the tolerance needed to be determined. The distance from the centerline to the center of the alignment mark is D2. The distance from the center of the alignment mark on the mask, to the alignment mark edge is E2

Designation	Description	Length (μm)		Tolerance (μm)	
		3 μm posts	5 μm posts	3 μm posts	5 μm posts
A2	Center layer 2 alignment mark to center of layer 2 pad	39	43	0	0
B2	Center of layer 2 pad to edge of layer 2 pad	3	4	± 0.4	± 0.4
C2	Edge of layer 2 pad to centerline of structures (GAP 2)	1.5	2.5	± 2.2	± 3.2
D2	Centerline of structures to center of layer 1 alignment mark	34.5	36.5	0	0
E2	Center of layer 1 alignment mark to edge of layer 1 alignment mark	10	10	± 0.4	± 0.4
F2	Edge of layer 1 alignment mark to edge of layer 2 alignment mark (alignment error)	0	0	± 1	± 2
G2	Edge of layer 2 alignment mark to center of layer 2 alignment mark	10	10	± 0.4	± 0.4

Figure 4.4. Second layer (constantan wiring) tolerance loop.

($\pm 0.4 \mu\text{m}$). The distance from the edge of the alignment mark on the substrate to the edge of the alignment mark on the mask is F2. This should be a fixed distance, normally the mark on the mask or on the substrate is designed to be bigger or smaller so that it can be seen through the mask, and the tolerance is the error due to alignment of the mask to the substrate. Sample post deposition with alignment was done to test what alignment error could be expected with the equipment available and is covered in the next section. The distance from the edge of the mask alignment mark to the center of the mask alignment mark ($\pm 0.4 \mu\text{m}$) is G2.

The remaining layers were analyzed in the same way (Figure 4.5 and Figure 4.6). All of the subsequent layers were aligned to alignment marks on the first layer.

In addition to the gaps between layers, there were also several other critical dimensions that had to be accounted for to insure that the device functioned properly. These dimensions are shown in Table 4.1. The minimum values for the dimensions were determined by calculating the left or rightmost possible points of the two features the gap was in between, using worst case tolerance values. The spacing and size of different features were changed until the critical dimensions were all greater than zero. For example, in the sixth critical dimension, it was important to ensure that the two posts did not touch until

Designation	Description	Length (μm)		Tolerance (μm)	
		3 μm posts	5 μm posts	3 μm posts	5 μm posts
A3	Center of layer 3 alignment mark to center of layer 3 post	30	30	0	0
B3	Center of layer 3 post to edge of layer 3 post	1.5	2.5	± 0.4	± 0.4
C3	Edge of layer 3 post to centerline of structures (GAP 3)	3	4	± 2.2	± 3.2
D3	Centerline of structures to center of layer 1 alignment mark	34.5	36.5	0	0
E3	Center of layer 1 alignment mark to edge of layer 1 alignment mark	10	10	± 0.4	± 0.4
F3	Edge of layer 1 alignment mark to edge of layer 3 alignment mark (alignment error)	0	0	± 1	± 2
G3	Edge of layer 3 alignment mark to center of layer 3 alignment mark	10	10	± 0.4	± 0.4

Figure 4.5. Tolerance analysis loop for layer 3.

Designation	Description	Length (μm)		Tolerance (μm)	
		3 μm posts	5 μm posts	3 μm posts	5 μm posts
A4	Center layer 4 alignment mark to center of layer 4 post	39	43	0	0
B4	Center of layer 4 post to edge of layer 4 post	1.5	2.5	± 0.4	± 0.4
C4	Edge of layer 4 post to centerline of structures (GAP 4)	3	4	± 2.2	± 3.2
D4	Centerline of structures to center of layer 1 alignment mark	34.5	36.5	0	0
E4	Center of layer 1 alignment mark to edge of layer 1 alignment mark	10	10	± 0.4	± 0.4
F4	Edge of layer 1 alignment mark to edge of layer 4 alignment mark (alignment error)	0	0	± 1	± 2
G4	Edge of layer 4 alignment mark to center of layer 4 alignment mark	10	10	± 0.4	± 0.4

Designation	Description	Length (μm)		Tolerance (μm)	
		3 μm posts	5 μm posts	3 μm posts	5 μm posts
A5	Center layer 5 alignment mark to edge of layer 5 junction	34.5	36.5	0	0
B5	Edge of layer 5 junction to post to edge of layer 4 post	7.5	11	± 0.4	± 0.4
C5	Edge of layer 4 post to centerline of structures (GAP 5)	7.5	11	± 2.2	± 3.2
D5	Centerline of structures to center of layer 1 alignment mark	34.5	36.5	0	0
E5	Center of layer 1 alignment mark to edge of layer 1 alignment mark	10	10	± 0.4	± 0.4
F5	Edge of layer 1 alignment mark to edge of layer 4 alignment mark (alignment error)	0	0	± 1	± 2
G5	Edge of layer 4 alignment mark to center of layer 4 alignment mark	10	10	± 0.4	± 0.4

Figure 4.6. Tolerance analysis loops for layers 4 and 5.

Table 4.1. Final minimum dimensions for additional critical distances.

Gap	Schematic	Description	Reason	Final min. dimension (µm)	
				3 µm Posts	5 µm Posts
1		Right edge of layer 1 pad to left edge of layer 2 pad	Copper and Constantan pads should not touch	0.4	1.4
2		Left edge of layer 3 post to right edge of layer 1 pad	Copper pad should be in contact with Copper post	1.9	2.9
3		Left edge of layer 2 pad to right edge of layer 4 post	Constantan pad should be in contact with Constantan post	0.1	0.1
4		Left edge of layer 1 pad to right edge of layer 3 post	Copper pad should be in contact with Copper post	1.9	3.05
5		Left edge of layer 4 post to right edge of layer 2 pad	Constantan pad should be in contact with Constantan post	0.1	0.1
6		Right edge of layer 3 post to left edge of layer 4 post	Copper and Constantan posts should not touch	1.6	1.6
7		Left edge of layer 5 junction to right edge of layer 3 post	Copper post should touch junction layer	0.1	0.6
8		Left edge of layer 4 post to right edge of layer 5 junction	Constantan post should touch junction layer	0.1	0.6
9		Right edge of layer 3 post to left edge of layer 2 pad	Copper post should not touch Constantan pad	0.1	0.1
10		Right edge of layer 1 pad to left edge of layer 4 post	Constantan post should not touch Copper pad	1.9	2.9

the junction at the top connected them. From the tolerance loop for each level, the expected maximum and minimum position of the right side of the copper post and the left side of the constantan post were already known. This gave a value for the closest distance between the two posts in a worst case tolerance scenario. By adjusting design dimensions this value was made greater than zero, to ensure that the posts will not touch even under a worst case tolerance.

4.4.3. Post Alignment Testing

Tests were performed to determine, with some degree of accuracy, the actual alignment capabilities of the UV exposure equipment available. A mask was developed to measure the alignment of one post layer relative to another with a range of post and gap sizes (Figure 4.7). The procedure used to test

Figure 4.7. Post alignment test mask. (a) Full mask. (b) Test post structures with surrounding dummy structures. (c) Test post structures. Sizes ranged from 5 μm to 20 μm in 2.5 μm intervals, with nominal spacing after alignment of 5 μm to 25 μm also in 2.5 μm intervals.

alignment was to spin a 19 μm layer of AZ 4620 resist, expose a pattern of posts, develop, and electroplate copper into the holes. An aligned exposure was performed, and a second set of posts were electroplated. The patterns were analyzed with an SEM (Figure 4.8) to determine the alignment error. The alignment, after accounting for differences in actual post sizes, was within ± 0.5 microns at the 5 μm posts with 5 μm gap, once the procedure was optimized.

With the small number of leads on the prototype device, it was possible to fit two separate 3x3 arrays on a single silicon wafer. Conservative and less conservative designs were used for the two arrays for the final device fabrication. Although alignment was shown to be within $\pm 0.5 \mu\text{m}$ in the post tests, a value of $\pm 2 \mu\text{m}$ was used in the final tolerance analysis as a conservative case, and a value of $\pm 1 \mu\text{m}$ was used in a less conservative case, because of the human

Post group	1 st Post diameter at base (μm)	2 nd Post diameter at base (μm).	Actual gap (μm)	Adjusted expected gap (μm)	Alignment error (μm)
a	4.6	6	4.9	4.7	+0.2
b	4.6	6	5.2	4.7	-0.4
c	4.5	5.4	5.3	5.1	+0.2
d	4.5	5.2	5.3	5.2	+0.1

Figure 4.8. Post samples for alignment testing. The first exposure is on the left.

factor in alignment and the likelihood of structures being larger than the mask patterns. The final dimensions for both cases included in the tolerance analysis and used in the photomasks are shown in Figure 4.9.

4.5. Electrodeposition

Constantan (copper-nickel) and copper thermocouples (type-T) were chosen as the thermocouple type for the device because the copper-nickel alloy is easier to electrodeposit than any of the other standard alloys used in thermocouples, the Seebeck coefficient is stable at low temperatures, and it offers excellent sensitivity below 0°C (ASTM, 1970). The next few sections give a brief background on electrodeposition, outlines electrochemical factors considered in fabrication and describe experiments done to obtain the proper plating solution and parameters.

4.5.1. Background

For a particular electrodeposition cell setup (bath composition, cell and electrode geometry, and other factors) the relationship between the voltage and

Figure 4.9. Top view of final dimensions used in tolerance analysis and final design.

the current of the system is represented by a polarization curve. This curve contains useful data about an electrochemical system, especially for alloy deposition. Figure 4.10 is an example of a copper-nickel polarization curve. When a voltage is applied between the anode and cathode, the measured current density is given by the combined curve in the figure. The real benefit of studying the polarization curve in alloy deposition is being able to separate the individual curves of the elements in the alloy to determine their plating characteristics. In the example curve there is a copper and nickel curve as well as a curve for hydrogen evolution, a side reaction occurring at higher overpotentials that decreases efficiency. The relative amount of a single component element deposited in an alloy is based on the relative proportion of

Figure 4.10. Sample polarization curve for copper and nickel alloy deposition. Shows overall combined curve, as well as partial current curves of copper, nickel, and hydrogen evolution.

the total current density curve coming from the curve for that element. Knowing the trend of individual component curves can aid in predicting deposition composition for alloys.

The rate of material deposited is based on the current efficiency and Faraday's law (Eq. (4.1))

$$It = nF \left(\frac{m}{sM} \right) \quad (4.1)$$

Here, I is the applied current, t is the time length of deposition, n is the number of electrons in the reaction, s is the stoichiometric coefficient in the balanced reduction equation, M is the molecular weight, F is Faraday's constant (96,485 Coulombs/mole) and m is the mass reacted. The actual rate is generally smaller because not all of the applied current goes toward depositing the metal; the efficiency is less than 100 %.

In this project, a specific composition of two metal species was required, and it was important to pay attention to what current was being used to electrodeposit, and also which section of the curve was in use. From Figure 4.10, there is a thermodynamically-controlled reversible potential at the start of the curve, a kinetically controlled upward sloping region, and a flat mass transport controlled region. Generally, regions are mixed, such that the curve is not governed just by mass transport or just by kinetics.

At equilibrium, no current is applied, and the reaction is at its reversible potential along the x-axis of the graph. This reversible potential is based on the standard potential, which is a constant for a particular oxidation or reduction of an ion, modified by thermodynamic solution factors. Electrons will normally try to go

to the most favorable, lowest energy, state, and remain there. For example, if iron is placed into a solution of CuSO_4 , the copper will replace the iron on the surface, because it is a more favorable energy state for the electrons. Applying a current will help to move a reaction out of the unfavorable range and allow reactions that normally would not happen to take place.

Once a current or voltage is applied, the relationship between current and voltage is governed by the rate of electrochemical charge transfer. For electrodeposition onto a substrate, this reaction is governed by the Butler-Volmer equation for a cathodic process (4.2).

$$i_c = -i_0 e^{\frac{-\beta n F \eta}{RT}} \quad (4.2)$$

Here, i_0 is the exchange current density, β is the reaction rate, R is the gas constant, T is the temperature, η is the overpotential. Overpotential is the voltage deviation from equilibrium or the reversible potential. The exchange current is the back and forth exchange of charge carriers going on in the system even during equilibrium. Deposition in this zone is kinetic and current rises exponentially with an increase in overpotential.

When the current is large enough, depending on the solution concentration, mixing, and geometry, mass transport dominates (Figure 4.10). The zero slope in the partial current curve during mass transport indicates that although the potential in the reaction may be increased, the current at which the species are reacted and the rate of deposition remains the same. This is called the limiting current, and it occurs because mass transport is limiting the reaction.

At lower currents, in the kinetic region, the surface concentration of ions is approximately equal to the bulk concentration. At higher currents, the deposition rate is more rapid, and the ions are not replaced quickly enough on the surface. This creates the mass transport limitation, where the surface concentration is not equal to the bulk ion concentration.

In the plating cell, more current simply increases the amount of hydrogen evolution, and not species deposited (efficiency goes down). The limiting current is affected by mixing in solution, rotating the working electrode, as well as species concentration in the solution.

The diffusion layer is the distance from the electrode, generally several micrometers size, where the local ion concentration is smaller than the bulk concentration. Within this layer, there are three main modes of mass transport: diffusion-based transport governed by species concentration, convection-based transport governed by solution velocity, and migration-based transport governed by the electric field. In electrochemical cells, migration can often be neglected, and the diffusion layer can be simplified into a linear Nernst diffusion layer near the electrode, where diffusion is assumed to play the main role, and the remaining space where convection is dominant. The limiting current can then be approximated by Equation (4.3).

$$\frac{i_{lim}}{nF} = D \left(\frac{C^b}{\delta_N} \right) \quad (4.3)$$

Here, i_{lim} is the limiting current, D is the diffusion coefficient for the solution, C_b is the bulk ion concentration and δ_N is the Nernst diffusion layer distance. This equation assumes that the surface concentration, C_s is 0.

Equation (4.3) shows that a smaller diffusion layer gives an increased limiting current, which also means there is an increased concentration slope near the surface. In electrodeposition of microstructures, this is important because the Nernst diffusion layer is approximately equal to the depth of the recess during deposition. The implication of this is that if one is electroplating at or near the limiting current of a species, as the plating progresses, and the depth decreases, the limiting, and plating, current should change. If one is performing alloy deposition, then this leads to the very real possibility of nonuniformity of plating along the height of the microstructure. For this reason, it is ideal to have both species of the system under kinetic control. For copper and nickel this task is not so easy because of the disparity in standard potentials, 0.34V for Cu and -0.25V for Ni vs the normal hydrogen electrode (NHE). The copper-nickel solution was adjusted to achieve kinetic electrodeposition.

4.5.2. Copper-Nickel Deposition Background

Nickel and copper can be a somewhat difficult alloy to deposit uniformly because the standard potentials are quite different. For this reason, it is useful to have a bath additive to complex with the species and bring the potentials closer together (Panda, 2004). For the fabrication of the thermocouples for this device, a citrate and ammonia complexing solution was chosen.

Many studies have been done on citrate copper nickel solutions. Modeling and experimentation by Podlaha, et al. (1994) found that partial current densities are reduced by the citrate complexing for both nickel and copper, but by different amounts. In addition, when citrate is used as a complexing agent, it has

been shown to give smoother microstructures, act as a leveling agent, a brightening agent, and a buffering agent (Panda, 2004). Green, et al. (1998) determined that the pH is important in terms of the solution stability, with greater stability at higher pH, having tested pH's of 4 and 6 adjusted with NaOH.

Ammonia was chosen for the solution because it also complexes with copper and nickel and can help to shift copper to less noble potentials and to improve the deposition of the desired alloy. Chassaing, et al. (1986) performed experimental studies that determined that the copper deposition is inhibited by the complexing of ammonia, leading to a more nickel rich deposit.

Electrodeposited type-T thermocouples have not been extensively studied in the past, but some work has been done. Copper and constantan thermocouples were fabricated through electrodeposition by Taherian and Hosseini (2004), though not at the microscale. Tests on thermopower of electrodeposited copper-nickel alloys were reported by Bakoni, et al. (1998).

4.5.3. Plating in Recesses

In recessed deposition plating, there are concerns about mass transport limitations and pH increase at the surface. When a potential is applied to a micropatterned substrate, the pH will increase at the surface with time and can negatively affect the growth of microstructures (Panda, 2004). Pulse plating can be used to give a relaxation time to bring the pH back down and allow any hydrogen gas formed during electrodeposition to escape from the surface of the electrode (Panda, 2004).

Panda did research into electrodeposition of copper-nickel alloys into deep recesses from citrate electrolytes and ammonia at high pH. For his structures, nickel was kept in great excess of the copper, leaving copper as mass transport controlled, and having a variation of copper concentration along the height of the post. The solution used in this device is a modified version of Panda's solution that enables kinetic control of both copper and nickel deposition.

4.5.4. Plating Along the Surface Uniformly

4.5.4.1. Electric Field Lines

In addition to mass transport and kinetics, the electric field in a plating cell can also limit the reaction rate on parts of the substrate. Fields can have a strong effect when mass transport is not a limiting factor, and kinetics are fast (higher parts of the kinetic region). These field lines are based on the orientation of the anode, cathode and the plating cell. They tend to concentrate at certain points, and cause local current densities to be higher or lower than the overall average. This causes nonuniformity in deposition along the surface of an electrode. For example, if field effects are strong, and parts of the working electrode are further than others from the anode, the orientation is not completely parallel, the deposition will be greater at places on the cathode that are nearer and less at places farther away. In addition, current tends to be greater at the edges of the cathode, and in the case of an anode larger than the cathode, this can be more pronounced. Recessed electrodes (micro or macroscale) can provide a more uniform current distribution at the edges.

4.5.4.2. Wagner Number

When the current distribution is based on field effects, it is known as a primary current distribution. When kinetics limit the distribution along with field effects it is called a secondary current distribution. The Wagner number is useful when a secondary current distribution dominates; it relates kinetic effects to electric field effects (Equation (4.4)):

$$Wa = \frac{\kappa}{L} \left(\frac{d\eta}{di} \right) \quad (4.4)$$

where κ is the conductance, L is the characteristic length, and $d\eta/di$ is the change in overpotential with change in current, which is also the inverse of the slope of the polarization curve. If the inverse of the slope is small near the beginning of the polarization curve, then the Wagner number is large. Most of the resistance comes from charge transfer, so kinetics are slow. Field effects do not play a large role, and the distribution is more uniform along the surface. As the inverse of slope increases, higher into the kinetic region, the charge transfer resistance decreases, (faster kinetics) and the ohmic resistance becomes dominant, meaning field effects play a greater role. This leads to a secondary current distribution where both kinetics and field effects are important. In the limiting case, where the Wagner number goes to 0, the system has a purely primary current distribution, based solely on electric field effects, and the surface current distribution can be very nonuniform. The implication is that it is beneficial to have a system with a high Wagner number to increase uniformity. This can be achieved by depositing at a very low current or at the limiting current. For the solution used in these experiments, this is a problem. For post deposition it is

important to optimize the solution so that a an appropriate copper nickel ratio is achieved in the kinetic region. Copper and nickel experiments showed that a high current density was required. It was well into the kinetic region, where kinetics are fast and field effects dominate. Having deposition uniform in the posts hinders the ability to have uniformity along the surface for the wiring layer. Since plating at a low current or at the limiting current is not possible, another option is to make the electric field more uniform.

4.5.4.3. Active Area Density

The way resist is micropatterned on a substrate can have a large effect on the plating uniformity. Current goes in the direction of least resistance, and so from a distance field lines will bend towards the areas with a higher density of exposed metal when Wa number is low. At the feature size, these lines will bend together and go to the patterned areas. By treating patterned areas as an active area density (AAD), or a ratio of actual available area over projected area (Mehdizadeh, et al., 1992), rather than accounting for individual micro-features, it simplifies analysis of a substrate, and allows for easier comparisons in determining trends in the deposition uniformity (Mehdizadeh, et al., 1992).

4.5.4.4. Auxiliary Electrode

An auxiliary electrode, or thief, can be used to make current distribution on a substrate more uniform. When the electric field effects are prominent, the current density will be greater at the edge of a substrate. If a sacrificial electrode that is in electrical contact with the substrate can be placed around the edge, the

greater current density will go to the auxiliary electrode, and the substrate deposition will be more uniform.

Past research has been done with patterned substrates and auxiliary electrodes. Choi and Kang (1996) found there is an optimum size of the auxiliary electrode for different active area densities. If the auxiliary electrode is too large, the current density at the edges of the patterned area can drop below the center current value. Results by Choi and Kang (1996) have also shown that with a smaller active area density, current distribution from the center to the edge of the substrate is more uniform.

Mehdizadeh, et al. (1992) modeled patterned electrodes with and without a thief. With a non-uniform AAD and no thief, higher Wagners number gave better uniformity. Their research also showed that with a thief, a uniformly patterned electrode actually gave more uniform current distribution than a bare electrode. For a non-uniform patterned electrode, the results show that a thief can help surface current distribution. Conclusions from the studies showed that using a low plating rate, a bath that was very conductive, a small polarization curve slope, and a low average active-area density all lead to better uniformity. In addition, small spatial variations of active-area density, avoiding abrupt variations in AAD, and small distances over which variations occurred, avoiding variations over the entire work piece, also improved uniformity.

Oh, et al. (2004) used modeling and experiments to study the effects of several different factors on plating uniformity. Their research showed that there is an optimum value for the size of the auxiliary electrode and also for the

distance between the auxiliary electrode and the patterned substrate, though a smaller distance was generally shown to be better in terms of plating uniformity. They also observed that the best uniformity occurred when the anode was the same size as the cathode and that the distance between anode and cathode can affect uniformity.

4.5.5. Electrodeposition Experiments

Several electrodeposition experiments were performed to determine a solution composition and applied current density for uniform post composition, as well as composition along the length of the wire layer for copper-nickel deposition.

4.5.5.1. Flat Plate Deposition Testing

Some preliminary experiments were done using deposition onto a flat plate to determine the effects of solution composition. The first solution was taken from Panda (2004) with a pH of 8. This solution precipitated after some time, so a second solution (A) was made with the same components, but with pH increased to 8.9 (Table 4.2). The mass percent composition of the deposits plated were obtained using energy dispersive X-ray fluorescence (EDXRF, Kevex Omicron, Atlanta, GA).

Table 4.2. Copper-nickel plating solution A, with pH adjusted to 8.9.

Solution Component	Composition
Nickel Sulfate	1.0 M
Copper Sulfate	0.004 M
Sodium Citrate	0.3 M
Ammonium Hydroxide	270 mL/L

Under flat deposition, it was difficult to get accurate results because the deposited composition would vary along the surface. However, some conclusions were reached from testing. The small amount of copper in the solution most likely indicated deposition with copper in mass transport control, but the nonuniformity along the surface of the flat plate indicated the nickel was still in the kinetic range. The places where the copper and nickel were in a favorable ratio produced rough, brittle deposits indicating hydrogen evolution. In addition, the solution was not stable unless there was enough ammonium hydroxide and sodium citrate added to complex the copper and nickel ions. This meant that the total number of moles of ammonium hydroxide and sodium citrate should at least equal the number of moles of copper and nickel ions. Several of the attempted solutions precipitated for of this reason.

The solution was modified and more tests were performed. The amount of nickel sulfate was decreased, and the copper sulfate was increased, in an attempt to move the composition away from areas of high hydrogen evolution. The citrate and ammonium hydroxide amounts were increased in order help shift the partial current curve for copper towards the nickel curve to aid in deposition of both copper and nickel in the kinetic region. The results still showed a great deal of variation over the surface of the flat plate, and overall the data was inconclusive. However, data revealed that extremely high pH's (9-11) did not give good results. A first impression would be to add as much ammonia as possible to move copper more favorably, but results showed that deposits with

high nickel content were rough and brittle. A rotating Hull cell (Brinkmann Instruments, Westbury, NY) was then used to obtain more useful data.

4.5.5.2. Rotating Hull Cell Testing

4.5.5.2.1. Background

One of the tools used to help find a solution that is kinetically controlled is the rotating Hull cell. The device is based on combining two principles: the Hull cell and the rotating cylinder electrode (Madore, 1993).

The Hull cell is a trapezoidal shaped plating cell where the cathode is at an angle to the anode, which creates a distribution of current along the surface due to electric field effects (primary current distribution). In this plating cell, a local current density along the cathode can be determined from a known average applied current density. This means that a range of deposition currents can be tested from a single experiment.

A rotating cylinder electrode (RCE) allows one to know the boundary layer thickness for mass transport based on the speed of the rotation, using the Eisenberg relation (4.5).

$$\delta = 99.62d^{-0.4}\nu^{0.344}D^{0.356}S^{-0.7} \quad (4.5)$$

Here d is the diameter of the RCE, ν is the solution viscosity, D is the diffusion coefficient of the solution and S is the rotation rate of the RCE. For a micro-electrodeposition study, this allows one to relate rotation rate on the RCE to recess depth by applying Eq. (4.3), and therefore simulate the recessed plating conditions without a recessed substrate. The Rota-Hull cell (Figure 4.11), based on the orientation of anode and cathode, gives a distribution of current along the

Figure 4.11. Rotating Hull cell schematic

length of the cylinder, similar to a Hull cell, as well as allowing for relating rotation rate to recess depth. The main benefit of using the Rota-Hull is that it allows testing multiple current densities with a single experiment.

4.5.5.2.2. Testing

Several experiments were run with a rotating Hull cell with different solutions and rotation rates. Deposition experiments were performed on stainless steel cylinders to facilitate testing of composition since the substrate contained neither copper nor nickel. Rotation rates of 150, 400 and 600 rpm were used in the experiments which correspond to 100, 50 and 35 μm recess depths, respectively.

The samples were put into the rotating Hull cell, and an average current density was applied. Based on the manufacturer's data, the ratio of local current to average current density was known at each point along the cylinder. Using energy dispersive X-ray fluorescence (EDXRF), the compositions at several points along the cylinder were analyzed, and plotted against the current densities expected at those points.

A new solution (B) was tested (Table 4.3), by modifying Panda's solution to increase copper content and citrate content but keep the pH below 9. Figure 4.12 shows a plot of copper concentration with respect to local current density for this solution. The curves are shown corresponding to 100 μm , 50 μm and 35 μm recess depths. In an ideal case, the three curves would be almost identical, indicating recess depth, or mass transport effects, do not influence composition. Although there is some similarity between curves, in places there is a disparity of as much as 20% in composition, indicating that the deposition was at least partly mass transport controlled.

In order to obtain kinetic control through the desired composition region, the solution was modified, with greatly increased copper and sodium citrate

Table 4.3. Copper-nickel plating solution B, with pH adjusted to 8.

Solution Component	Composition
Nickel Sulfate	1.0 M
Copper Sulfate	0.15 M
Sodium Citrate	0.75M
Ammonium Hydroxide	46.5 mL/L

Figure 4.12. Copper composition curve for solution B.

concentrations (Table 4.4). Figure 4.13 displays copper concentration with respect to current density for the same three recess depths. For this solution (C), a much more uniform composition was obtained, although compositions with an adequate amount of nickel required much higher current densities than the previous solution.

Table 4.4. Copper-nickel plating solution C and D components. The pH was 8.1 for solution C and 6.8 for solution D.

Solution Component	Composition
Nickel Sulfate	1.0 M
Copper Sulfate	0.5 M
Sodium Citrate	1.0 M
Ammonium Hydroxide	74 mL/L

Figure 4.13. Copper composition curve for solution C.

Bulk constantan composition is normally considered 55% copper and 45% nickel. Research has been done with electrodeposition of constantan (Delatorre, et al., 2003; Bakonyi, et al., 1998) that showed good thermopower between -25 and -45 $\mu\text{V/K}$ for compositions between 30 % and 60 % copper. Ideally, the deposited composition can fall within this range throughout the height of the post, so it can have a good, relatively uniform thermopower.

Another plating solution was made, using the same proportions of reagents, however the pH was 6.8. The reason for this is unclear, but it may be the result of using old ammonium hydroxide or impure DI water for the first curve. A solution with a pH closer to 8.1 was attempted (by adding more ammonium hydroxide) but the results were not favorable. A series of rotating Hull cell

experiments were performed for the pH 6.8 solution (D), and the results showed similar shaped curves to solution C, with concentrations slightly offset (Figure 4.14). Solutions C and D show much improved uniformity over solution B, with generally less than 10% composition change between curves, with some variation at higher current densities. In general, uniformity in composition should be best with small micropatterned recess depths, but the curves show sufficient uniformity, even at 100 μm depths.

The results point out that these final two solutions allow electrodeposition in the kinetic region for both nickel and copper, leading to a more predictable and uniform deposit in micropatterned recesses. The drawback was that concentration had to be increased for copper, which led to higher current

Figure 4.14. Copper composition curve for solution D.

densities required for a nickel rich deposit. This can lead to hydrogen evolution, and may require pulse plating for recessed deposition.

4.5.5.3. Wiring Deposition Testing

Some final tests were done to test the uniformity of plating along the surface of a micropatterned substrate for the wiring layer of the device from this solution. Tests were performed for deposition with different size thief electrodes and without a thief to determine the compositions near the micropatterned features and near the points of connection with the patterned circuit board. Figure 4.15 displays the jig used along with the thieves tested for these experiments. A large thief (13 mm from inner diameter to outer diameter) was designed to reach to the edge of the sidewall on the jig. Two successively smaller sizes of 6.5 mm and 3.25 mm were also tested. Figure 4.16 shows the

Figure 4.15. Jig and auxiliary electrodes used in wire testing deposition. (a) patterned 10 cm wafer. (b) 13 mm (ID to OD) thief. (c) 6.5 mm thief. (d) 3.25 mm thief. (e) Jig base. (f) Jig cover. (g) Assembled jig with patterned wafer and 13 mm

experimental setup for the electrodeposition. A platinum coated titanium mesh counter electrode was used in the experiments, along with a mechanical stirrer to provide agitation. A horizontal substrate orientation was used so that any gases formed during deposition would be able to escape from the surface easily.

Table 4.5 lists the results of the experiments. Analysis was performed quantitatively with energy dispersive spectroscopy (EDS), and the error may be 10%-20% or more, but general trends can be observed. One point is that using a thief did not necessarily improve the deposition uniformity. There was a much larger disparity in the thickness of the deposited material between the center and edges when a thief was used. The hypothesis for this result is that the way the

Figure 4.16. Experimental setup for wire deposition testing.

Table 4.5. Comparison of Coper composition in constantan wiring layer for different current densities and thief sizes.

Thief Size (mm)	Current Density (mA/cm ²)	Deposition time (s)	Center height (μm)	Center Cu concentration (wt%)	Outside edge height (μm)	Outside edge Cu concentration (wt%)
13	20	60	3.35	50	0.4	60-75
6.5	50	90	8.0	33-43	1.0	33-55
3.25	50	120	5.0	40-50	1.5	66
None	40	90	2.4	75-80	1.3	50-60
None	50	45	1.75	66	1.5	30-40
None	60	45	2.25	40-50	1.0	33
None	70	45	2.5	40-50	1.0	20-30

wiring layer was designed (covered in the next section), with the wire traces gradually increasing in size with increasing distance from the center of the wafer, helped to make the current distribution more uniform, and a thief was not necessary.

Plating at a current density of 60 mA/cm² provided the best composition uniformity, though with a somewhat higher than optimal nickel content. In addition, within the channels of the wiring, the deposit was U-shaped, with a greater current density along the edges of the length of the wire. This also showed that field effects were prominent and raised a concern about plating at the center, where wire spacing was very small (~3 μm). The overplating at the edges happened quickly, and limited the thickness of the constantan deposit in the middle without touching neighboring wires.

4.6. Mask Design

4.6.1. Mask Concerns and Design Goals

In designing the UV photomask for each layer in the device, the main concerns were alignment and current uniformity during electrodeposition. The main requirements in alignment have been detailed in the sections on tolerance analysis. The results of these studies gave proper values for spacing and sizes

of the microfeatures that would ensure the device would be fabricated successfully. The remaining concerns were designing the alignment marks and designing the masks for good current uniformity in deposition. A complete layout of the masks used in fabricating the device can be found in Appendix A.

A radial pattern was chosen for the arrangement of the thermocouple wires and the reference junctions' connection to the PC board (Figure 4.17). This was to keep the reference junctions of the thermocouples on the same isotherm which would allow a single macroscale reference temperature thermocouple to measure the temperature of all of the reference junctions.

4.6.2. Alignment Marks

Alignment marks were used on the masks to properly orient one layer with another. All of the successive layers are oriented to the first layer. The first

Figure 4.17. Radial pattern for copper and constantan wiring layers, for two separate 3x3 arrays. Top half is with 5 μm posts, and bottom half is with 3 μm posts.

mask has a set of base alignment structures that were exposed and developed in the resist for alignment of successive masks, which have features that visually correspond to these structures for alignment (Figure 4.18). The mask is a darkfield mask, so care must be taken to ensure that the developed base structures can be seen through the alignment marks on the mask. Several different sizes of marks were used to aid in alignment, to allow the best mark to be used when aligning. The size difference between the marks was kept small in order to allow very fine optical alignment. When alignment marks have a large difference in size, it is difficult to align to a high degree of accuracy. The alignment marks for the device masks used nominal half width size differences of 10, 7.5 and 5 μm between the base and mating structures.

4.6.3. Current Uniformity Along Substrate Surface

To aid current uniformity along the surface of the wiring layer mask, a gradual increase in wire size from the point of the measuring junction to the

Figure 4.18. Alignment marks on the photomasks. (a) marks for first layer of device for forming alignment structures in resist. (b) Second layer mating alignment marks.

reference junction was used. This prevented sudden changes in active area density, which can cause nonuniformity.

For the post and junction layer masks, no extra structures were used to aid in current uniformity, instead, it was assumed that the best current distribution would be achieved by only leaving the necessary structures in the design. A sacrificial area (Figure 4.15d) was used around the edge of the patterned area in order to increase the overall plating area and allow better control of the current density.

4.7. Device Fabrication

4.7.1. Wafer Preparation

The microfabrication was performed on a silicon wafer. It was important for the wafer to have high electrical resistivity along the surface, to ensure that the wires on the surface of the device were adequately insulated from each other. For fabricating the device, two types of silicon wafers were tested, one with a 4.5 μm SiO_2 layer and another with high resistivity of 63-77 $\Omega\text{-cm}$ were used. A 0.01 μm titanium adhesion layer and then a 0.05 μm copper plating base were e-beam evaporated onto the surface of the silicon wafer. The wafer was then dehydration baked at 95 $^{\circ}\text{C}$ on a hot plate for 5 minutes to promote adhesion of the resist with the substrate.

4.7.2. Wiring Layer

S1813 positive photoresist was used for the patterning the wiring layers. Approximately 20 ml of resist was poured on the surface of the substrate, and spun at 2000 rpm for 60 seconds. The sample was baked for 90 seconds at 95

°C on a hot plate. The sample was exposed with vacuum contact on a Quintel UL7000-OBS Aligner and Exposure station (Quintel Corp., Morgan Hill, CA) with a dose of 75 mJ/cm² at the 365 nm wavelength. It was important to insure high vacuum contact in order to keep the features exposed in the resist as close as possible in size to the features on the mask. The resist was developed with MF-321 Developer (Rohm and Haas, Philadelphia, PA) for 120 seconds. After development, the sample was rinsed with DI water and blown dry with nitrogen gas (Figure 4.19a). The processing parameters for the S1813 resist were taken from manufacturer's recommendations (Shipley, Inc., Marlborough, MA) modified through testing.

A small amount of DI water, approximately 5 ml, was placed over the center of the micropatterned structures, and the sample was placed in a vacuum chamber (Nalge Nunc International, Rochester, NY), and depressurized with a vacuum pump (Emerson, St. Louis, MO) for 6 minutes to remove any air bubbles from the small patterned areas of the wiring layer. The sample was electroplated, using the same jig and setup as for the wire deposition testing

Figure 4.19. Copper wiring layer fabrication. (a) After exposure and development. (b) After copper deposition.

(Figure 4.16), without an auxiliary electrode. The solution used for the copper wiring layer is given in Table 4.6. Plating was done galvanostatically, at 7 mA/cm² for 12 minutes. After electroplating, the sample was thoroughly rinsed with DI water and dried (Figure 4.19b). It was important to insure that the current was started as soon as possible once the sample was in the plating bath because the copper plating base was etched by the solution when the sample was in the solution and no current was applied.

Next, a layer of S1813 resist was spun over the first layer of resist in order to cover the exposed copper wiring, and prevent electroplating on the copper during the copper-nickel electrodeposition. The alignment marks were covered with polyester tape (100 µm thickness, Harman Corporation, Rochester, MI) so that the second resist layer would not obscure the marks and make future alignments difficult. The resist was spun at 2000 rpm for 60 seconds. The polyester tape was removed prior to prebaking, since it was discovered that leaving the tape on the resist during the baking step left a residue which hindered visual alignment. The sample was baked at 95 °C for 90 seconds. The second wiring layer mask was aligned to the base layer and exposed under vacuum contact on the Quintel exposure station, with a dose of 75 mJ/cm² at 365 nm. It was developed for 120 seconds in MF-321 developer (Figure 4.20a). The

Table 4.6. Copper plating solution components.

Solution Component	Composition
Copper Sulfate	1.0 M
Sulfuric Acid	100 mL/L

sample was again placed in a vacuum chamber and depressurized to remove air bubbles and electroplating proceeded with copper nickel solution D, using the same experimental setup as for the copper deposition. The applied current density was 60 mA/cm^2 , for 15 seconds. The sample was then thoroughly rinsed with DI water and dried with nitrogen gas (Figure 4.20b).

4.7.3. Post Layer

The vertical post intermediate layers helped to thermally isolate the thermocouple junctions from the wiring. The first step was to remove the thin resist that was already present. Spinning AZ P4620 resist over the thin S1813 resist layer was attempted, but did not give good results. The solvents in the unbaked AZ resist reacted with the layers below, leaving a surface that could not be used for further exposures. Therefore, the alignment marks were covered with aluminum foil, and a flat exposure over the entire surface of the wafer at 200 mJ/cm^2 at 365 nm was used on the Quintel exposure station. The foil was removed, and the resist was developed with MF-321 developer for 120 seconds, removing the resist from the wiring layer, and leaving the unexposed alignment

Figure 4.20. Copper-nickel wiring layer fabrication. (a) After exposure and developing. (b) After copper-nickel deposition.

marks intact. Next, the wafer was rinsed with DI water, dried, and baked at 95 °C for 5 minutes on a hot plate to remove any remaining water and improve adhesion of resist to the wafer. The alignment marks were covered with polyester tape during the spin coating of the resist.

The method for spin coating the resist for the intermediate post layer was taken from Yoon, et al. (1998). Since multiple exposures were required on a single resist layer for device fabrication, a positive resist was necessary. There are some negative resists, such as SU-8, that are well suited for thick coats and tall microstructures, but to get thick structures with positive resists generally requires spinning multiple coats. Multiple coats lead to longer process times, more opportunities for problems and suboptimal exposure results. Yoon, et al. reported a technique to spin positive resist in thick layers with a single coat by using high spin speeds and very short spin times. The spin speed used was 2000 rpm for 5 seconds for a nominal 20 µm post height, with actual results between 18 µm and 19 µm across the wafer surface.

After spin-coating, the edge bead was removed by hand with a flat glass plate, and the polyester tape was removed from the alignment marks before prebaking. The sample was given a 10 minute relaxation time before being soft baked in a convection oven (M326 mechanical convection oven, Blue M Electric, Watertown, Wisconsin) for 10 minutes at 85 °C, and then baked again on a hot plate at 115 °C for 60 seconds. The sample was baked on a glass holder on the hot plate such that there was an air gap between the middle underside of the wafer and the hotplate, and the top was covered. This method was

recommended by Yoon, et al. (1998) for improved sidewalls on developed structures. The high temperature bake was experimentally found to improve aspect ratio, but also reduced exposure sensitivity, so it was kept short. The air gap prevented sudden heating at the base of the resist, which caused thermal stress, and the cover helped to maintain the proper temperature over the surface. After baking, the sample was allowed to cool for at least 20 minutes before exposure. The sample was aligned and exposed on the Quintel with an intensity of 600 mJ/cm^2 at 365 nm, with high vacuum to ensure good contact. The alignment marks were covered with polyester tape to keep them in good condition during development. The sample was developed for 4 minutes and 30 seconds in AZ 400K developer (AZ Electronic Materials, Somerville, NJ), diluted 4:1 with DI water, rinsed with DI water, and dried (Figure 4.21a).

The sample was placed in a vacuum chamber and depressurized for 15 minutes to remove air bubbles, and then the copper-nickel posts were deposited using the same electroplating setup as the copper-nickel wiring layer, except an additional sacrificial electrode (Figure 4.15d) was used to increase the area of deposition to allow for more precise control of current density. The actual local

Figure 4.21. Copper-nickel post layer fabrication (a) After exposure and developing. (b) After copper-nickel deposition

current density at the posts was difficult to know for certain, but experiments indicated that it was higher than the applied current density. When the same current density used for the constantan wiring layer was used to plate the posts, a heavily oxidized and uneven deposit formed over the posts (Figure 4.22). To alleviate this effect, the current density was reduced, and a pulse plating scheme, modified from Panda (2004), with a 0.25 duty cycle and 10 second on time was used. The current density applied was 15 mA/cm^2 for a total plating on-time of 20 minutes. The actual copper nickel composition of the resulting posts has not been tested. After deposition, the sample was rinsed with DI water and dried (Figure 4.21b).

The alignment marks were covered with polyester tape and a layer of S1813 resist was spun over the surface in order to prevent electroplating on top of the copper-nickel posts during the copper electrodeposition. The resist was spin coated at 2000 rpm for 60 seconds, the tape was removed, and the sample

Figure 4.22. Copper-nickel post deposition with oxide formation at high current density without pulse plating.

was prebaked on a hot plate for 90 seconds at 95 °C. The sample was aligned and exposed with the copper post layer on the Quintel exposure station with a 600 mJ/cm² dose at 365 nm with high vacuum contact. It was developed for 4 minutes and 30 seconds in diluted AZ 400K developer (Figure 4.23a). The sample was rinsed in DI water and dried, and depressurized for 15 minutes with 5 ml of water placed over the structures. For electrodeposition, the plating setup used was the same as for the copper-nickel posts, using the copper plating solution. The sample was plated at 7 mA/cm² for 1 hour and 15 minutes, rinsed with DI water, and dried (Figure 4.23b). Pulse plating was not necessary for the copper posts because of the lower current density applied and lack of noticeable oxide formation.

4.7.4. Junction Layer

The junction layer was exposed without spinning another layer of resist. The goal of the junction layer exposure was to expose an area of resist that connected the two posts, and maintain the exposure long enough so that the copper nickel post was exposed, but not so long that the area between the posts

Figure 4.23. Copper post layer fabrication. (a) After exposure and developing. (b) After copper deposition.

etched too deeply when developed. The sample was aligned and exposed with the final mask at 75 mJ/cm^2 at 365 nm on the Quintel exposure station, and developed for 2 minutes in MF 321 developer (Figure 4.24a). The sample was depressurized for 20 minutes, and the copper junction was electrodeposited with the same plating apparatus as the copper post layer. The plating was done at 7 mA/cm^2 for 45 minutes. After plating, the sample was rinsed with DI water and dried (Figure 4.24b).

4.7.5. Etching the Plating Base

After all of the layers were plated, it was important to separate the electrical connection between all of the wires by removing the copper plating base and adhesion layer on the wafer. The sample was first soaked in acetone to remove all of the resist on the surface of the wafer, though in the future, a flat exposure and development may be optimal to ensure complete removal. Next the sample was gently rinsed in IPA and dried. Before etching the copper base, SEM pictures were taken to examine the structures. Most of the junctions did not survive resist removal and rinsing, and most likely did not connect well enough from the two posts to create a stable structure (Figure 4.25).

Figure 4.24. Copper junction layer fabrication. (a) After exposure and developing. (b) After copper deposition.

Figure 4.25. Device after electrodeposition and resist removal. (a) View of 3 μm 3x3 array with reference temperature thermocouple on the right. (b) 3 μm 3x3 array. (c), (d) Closer views of successful thermocouple junctions.

The sample was placed in a commercial copper etching solution (Transene Company, Inc, Danvers, MA) to remove the copper plating base, for 10 seconds, and then immediately placed in DI water. To remove the titanium adhesion layer, the sample was etched in a 1% hydrofluoric acid solution for 10 seconds, and immediately placed in DI water. Afterwards, the resistance of the wires was tested to ensure electrical isolation of adjacent thermocouples. This was the final step reached in the microfabrication of the device. However, for actual use in cell temperature measurements, SU-8 would be cast around the microstructures, dissolved to the level of the junctions, and then given a flat UV exposure. A final working thermocouple array with an intermediate post layer

was not successfully fabricated. A thermocouple array without the post layer was finished, and this device was tested.

Table 4.7 compares the resulting final dimensions of two samples along with the design dimensions. The tolerances that were determined for the system were adequate in the final fabrication of the device. The wiring layers showed sizes very close to the design dimensions and even smaller in some cases, but the posts were greater in size than what was designed. More optimization would perhaps be able to bring the posts closer to the design sizes, but it is unlikely that they would match exactly. The actual alignment error was very good, and was less than 1 μm for all cases. This helped to compensate for the failure to include structure size increase during fabrication in the tolerance analysis.

4.8. Conclusions

The fabrication process chosen for the device was difficult to complete successfully. The small sizes and close tolerances required resist parameter

Table 4.7. Feature size and alignment accuracy for two fabricated samples.

		Sample 1				Sample 2				Ideal	
		3 μm post		5 μm post		3 μm post		5 μm post		3 μm post	5 μm post
		Size (μm)	Align Error (μm)	Size (μm)	Align Error (μm)	Size (μm)	Align Error (μm)	Size (μm)	Align Error (μm)	Size (μm)	Size (μm)
Copper wire		2.6	-	3.6	-	2.6	-	3.5	-	3	4
Copper pad		5.7	-	7.7	-	5.7	-	7.5	-	6	8
Copper-nickel wire		3.0	0.2	3.7	0.4	2.8	0.3	3.7	0.1	3	4
Copper-nickel pad		6.0	0.2	7.9	0.4	5.9	0.3	7.7	0.1	6	8
Copper-nickel post	Base	2.9	0.2	6.3	0.4	3.9	0.5	6.7	0.4	3	5
	Top	5.8	0.2	8.7	0.4	5.1	0.5	7.9	0.4	3	5
Copper post	Base	4.4	0.1	6.7	0.2	4.1	0.8	6.4	0.6	3	5
	Top	5.3	0.1	8.2	0.2	4.4	0.8	7.5	0.6	3	5
Copper junction		-	-	-	-	16.2	-	-	-	15	22

optimization for fabrication. Due to the nature of the multi-layer fabrication process, optimization on successive layers required substantial time, and left more room for mistakes during the procedure. The plating base and adhesion layer etching step was completed for only two samples, one on a high resistivity wafer, and another on a wafer with oxide. From the arrays on these two samples, only one thermocouple junction survived intact, though it was on the high resistivity wafer, which did not have sufficient electrical insulation to isolate the individual wires from each other. A sample without an intermediate post layer was fabricated on an oxide wafer, with 16 of 20 junctions fabricated successfully. This sample was tested and calibrated, with results presented in Chapter 5.

The fabrication of the junction layer of the device could be improved. Though the layer was intended to be only 2 μm thick, the same thickness as the copper wiring layer, the deposition took much longer than the copper wiring layer deposition. It took a significant amount of time to get the deposition on both posts to join together. One solution might be to e-beam evaporate a copper seed layer above the post layer and then spin and bake a resist to pattern the junctions on top of this layer. The junction plating would be uniform, and the remaining unplated seed layer could be etched away afterwards.

The removal of the plating base and seed layer was also an area that could be improved. When the resist layer was removed the, weak copper-nickel post to copper-nickel wiring layer adhesion caused some posts to separate from the sample. In addition, the remaining metal under the deposited wires means

that the thermocouple wires behave as a combination of the plated metal and the seed layer metal in terms of Seebeck coefficient.

One solution to this problem could be to etch the silicon wafer from the backside, without removing the resist surrounding the thermocouple junctions. This would require an additional temporary support for the sample, mounted on the top surface to sustain the structures while the wafer and plating base were etched away. Another solution might be to isolate the wiring and post layers for separate fabrication, and then passively align and assemble them. With this method, it may be possible to electrodeposit in the reverse order, with the junctions plated first and then the posts plated on top. The posts and junctions could be removed from the plating base, inverted and fixed onto the separate wiring layer.

5. Calibration and Testing

5.1. Instrumentation

Good signal acquisition and conditioning are required to obtain useful data from the thermocouple array. A printed circuit board (PCB), designed by Don Patterson of the Center for Biomodular Multiscale Systems (CBM²) was connected to the micropatterned wiring layer by a radial pattern of spring loaded gold contacts (Figure 5.1). These connections also formed the reference thermocouple junctions for the circuit. The goal of the instrumentation was to amplify and filter the small, microvolt level signal, compensate for the reference junction temperature, and provide the result in an accessible manner for analysis.

Figure 5.1. Interfacing of instrumentation and microfabricated device.

This chapter gives a brief outline of the signal processing and collection, sources of error, the method used for calibration, and the results of the calibration. Figure 5.2 is a block diagram of the circuit for the device. The different components involved will be explained in the next few sections.

5.1.1. Amplifiers and Multiplexing

Amplifiers were important in this system because the signal produced by the thermocouples was small and susceptible to noise. The standard sensitivity

Figure 5.2. Block diagram for the electrical system. The setup of the instrumentation allowed for two separate data inputs: One for the auxiliary thermocouple, and one multiplexed signal from each of the thermocouples in the array. The auxiliary thermocouple measured a voltage and the compensation thermocouple (1) was combined with it. The signal was amplified (2), then filtered (3), and amplified again (4). The thermocouples from the array were multiplexed and individual signals were combined with the compensation thermocouple (1), then amplified (2), and the auxiliary thermocouple signal was differenced from it and amplified. The new signal was filtered (3) and amplified again (4).

for a type-T thermocouple is approximately $38 \mu\text{V}/^\circ\text{C}$ between the reference and the measuring junctions (ASTM, 1970). The actual voltage generated was limited because the temperature difference between junctions could be one degree or less. The reference junctions were in close contact with the cooling area, and their temperature could be similar to that of the measuring junctions. The amplification was designed to be early in the circuit in order to limit the interference from noise.

In order for the amplifiers to work well in conjunction with data acquisition, an auxiliary microthermocouple was fabricated just outside of the thermocouple array (Figure 5.3). When a cooling rate is applied, this auxiliary thermocouple would experience the same temperature change as the array thermocouples. When a cell culture is placed on top of the array, the auxiliary thermocouple would be outside the range of heat generation from cell freezing. The

Figure 5.3. SEM picture of successfully fabricated micro-thermocouple array with auxiliary micro-thermocouple.

temperature from the auxiliary thermocouple is subtracted from the array thermocouples to isolate the temperature jump of freezing cells from the cooling rate. Once the signal is isolated, it is amplified 100 times to improve the reading of the signal. Without this differencing, the ambient temperature bias would saturate the amplifier under high gains.

Multiplexing allowed multiple signal inputs to go through the same circuit, in series, by switching between inputs, one by one. This permitted the use of fewer amplifiers and filtering circuits by sacrificing sampling rate. The time constant of cell freezing was estimated to be as small as 7.5 ms. The board allowed sampling rates of up to 250 Mhz, and multiplexing the thermocouples in the array decreased this value by a factor of nine, for each of the thermocouples in the array. If the sampling rate of the board was the limiting factor, 200,000 samples per time constant could be gathered. Multiplexing did not create any sampling rate limitations.

5.1.2. Reference Junction Compensation

In most modern thermocouple devices, the thermocouple reference temperature is near the point of connection between the thermocouple wires and a voltage measuring device. At this junction, there is normally a temperature sensitive resistor which compensates for the junction temperature, to give a reliable reading from the thermocouple (Horowitz and Hill, 1985). For this system, the reference junction location was dictated by the interface between the microfabricated components and the instrumentation—connected with the gold contacts—and it was not possible for the junction to be immediately adjacent to

the circuit. A commercial 0.076 mm diameter junction thermocouple (model 5TC-TT-T-40-36, Omega Engineering, Inc, Stamford, CT) was placed at the base of the circumferential arrangement of reference junctions, and connected to the circuit so it could be subtracted from the microthermocouple readings and compensate for the reference temperature (Figure 5.1). It was assumed that the temperature at each of these reference junctions was the same, being at the same distance from the center of the cooling element, as long as the sample was properly oriented on the cooling stage.

5.1.3. Noise Filtering

Preliminary testing showed that 60 Hz noise was dominant. Since the sensitivity of the thermocouple was low, and the difference in temperature between the measuring and reference junctions was expected to be small, a filter was important for obtaining a readable signal. The actual temperature jump would occur within 0.015 s, so it was necessary to use a notch filter around 60Hz rather than a simpler low pass filter.

5.1.4. Data Acquisition

The printed circuit board (PCB) was connected to a terminal box (Model SCB-68, National Instruments Corp., Austin, TX), capable of accepting eight differential analog inputs. The thermocouple array required two differential inputs, one for the multiplexed, differenced array data, and one input for the auxilliary microthermocouple. A PCI data acquisition board (Model PCI-6229, National Instruments) was used to interface from the terminal box to the

computer. LabView software (Version 7.1.1, National Instruments, Austin, TX) was used to control acquisition of the data.

5.2. Thermocouple Calibration

Calibration was important in this system because the electrodeposited CuNi (Constantan) was expected to have somewhat different thermoelectric properties than the bulk material. Previous work in electrodeposition has shown that the Seebeck coefficient for electrodeposited constantan differed from the bulk value (Taherian and Hoseini, 2004; Delatorre, et al., 2003; Bakonyi, et al., 1999).

5.2.1. Sources of Error

5.2.1.1. Nonuniformity in Wires

One of the assumptions made for determining temperature based on thermocouple voltage was that the wires in the circuit were all of uniform composition. When there is a change in composition, the thermocouple circuit behaves as if another junction between different metals is present.

Figure 5.4 shows three examples for determining the voltage generated in a thermoelectric circuit. The simplest case, where no voltage is generated, consists of a single metal with ends at two temperatures. There is a temperature gradient in opposite directions (from T1 to T2 and then back from T2 to T1); however, since the Seebeck coefficient is the same for both paths, the net voltage change is zero. Case 2 is the traditional thermocouple circuit. There are two metals, and two different temperatures at the junctions. There is a variation

Figure 5.4. Thermocouple voltage examples from different arrangements. (a) Case 1, single metal and two temperature junctions. (b) Case 2, two metals with two temperature junctions. (c) Case 3, four metals with four temperature junctions.

in temperature as well as Seebeck coefficient, and the EMF generated is based on the magnitude of both the temperature and Seebeck differences.

The final case is meant to illustrate the effect of nonuniformity in the thermocouple material. There is a nominal measuring junction of T1, and a reference junction of T2. The nonuniformity in deposited metals is represented as a discrete composition change with additional junctions T3 and T4 as a simplification from the actual gradual material change. The gradual uniformity change could be discretized as a series of many intermediate junctions, or more accurately as an integral. With the two additional junctions, there are four Seebeck coefficients, and four temperature junctions. Running through the loop of the different metals and then simplifying gives Equation 5.6 in Figure 5.4c. Assuming that the Seebeck coefficients are known for each metal, the voltage

generated (ΔE) and the reference junction temperature are known, there are still three unknowns: the measured temperature, T_1 , and the temperatures of the two auxiliary junctions, T_3 and T_4 ; so determining the actual measured temperature is impossible.

In a real experiment, the thermocouple will be assumed to behave as in Equation 5.4, when it may behave more like Equation 5.6. This nonuniformity distorts the measurements such that they depend on intermediate temperatures of the wires, which cannot all be known, and an uncertainty in the measurement and the Seebeck coefficient, exists because the wrong governing equation is assumed.

5.2.1.2. Standard Reference Thermocouple

Another source of possible error was from the thermocouple used to measure the temperature of the reference junctions. A standard type-T thermocouple was used to measure the reference junction temperature, and the voltage generated on this thermocouple was fed back into the processing circuitry for the thermocouple array. Although they were not analyzed, it was very likely that the electrodeposited thermocouples did not have the same Seebeck coefficient as the standard thermocouple. The difference in Seebeck coefficients between the standard and the electrodeposited thermocouples introduced some error.

For example, take the case where the microthermocouple sensitivity, Seebeck coefficient, is half of the compensation thermocouple sensitivity, $\alpha/2$ and α , respectively. When the measuring and reference junctions of the

microthermocouples are at the same temperature, the voltage reading is purely from the compensation thermocouple, and the correct temperature can be obtained from the measured voltage with α . If there is a temperature difference between the reference junction and measuring junction, the voltage generated is based on $\alpha/2$, and also on α . In this case, when the voltage measured is converted to a temperature based on α , the value would be off by half of the temperature difference between the reference and measuring junctions. In order to compensate for this, it would be necessary to know the temperature of the reference junction, in addition to implementing a reference junction compensation thermocouple.

5.2.1.3. Adhesion Layer and Seed Layer

A conductive layer was necessary to allow electrodeposition on the patterned substrate. Copper was chosen as the plating base only after flat plate deposition testing with titanium and gold showed poor results that did not match well with the Rotating Hull cell results. Titanium was required as an intermediate layer because of poor adhesion between copper and silicon.

In order to isolate the electrical connections of the individual wires, these two surface layers were etched away after all of the electrodeposition was finished, leaving only the copper and titanium directly beneath the copper and copper-nickel wires. This remaining copper and titanium changed the effective Seebeck coefficient of the wiring layer. Herin and Thery (1992) developed an equation for quantifying the effective Seebeck coefficient for layers of metals in

electrical contact. Applied to the system being studied, the equation can be written as Eq. (5.7).

$$\alpha_{eff} = \frac{\alpha_{CuNi}\sigma_{CuNi}t_{CuNi} + \alpha_{Ti}\sigma_{Ti}t_{Ti} + \alpha_{Cu}\sigma_{Cu}t_{Cu}}{\sigma_{CuNi}t_{CuNi} + \sigma_{Ti}t_{Ti} + \sigma_{Cu}t_{Cu}} \quad (5.7)$$

Here α is the Seebeck coefficient, σ is the electrical conductivity and t is the thickness of the respective layer. The same equation would apply to the copper wiring, with the CuNi terms removed. From the equation, it is clear that metals with high conductivity and thickness help contribute a greater portion of the Seebeck coefficient.

The thickness of the copper and especially the copper-nickel deposits were limited by the amount of overplating that was allowable. In order to properly fit both wiring layers, and eliminate electrical contact except at the junctions, the plating time had to be limited. Plating for Constantan tended to be much thicker at the edges and smaller at the center, forming a U-shaped deposit along the length of wire. Overplating on the edges occurred very quickly during electrodeposition, and the thickness of the Constantan deposit in the center was limited to around 0.4 μm . A thicker deposit would have been better, leading to more of the overall Seebeck coefficient coming from the copper-nickel deposit instead of the copper and titanium below. The effect was estimated by

Table 5.1. Material properties used with Eq. 5.7. Data from: ¹efunda.com, 2006; ²Worner, 1950; ³Wikipedi.org, 2006

	Seebeck coefficient, α ($\mu\text{V}/^\circ\text{C}$)	Electrical conductivity, σ (Ωm^{-1})	Thickness, t (μm)
Copper	65 ¹	5.95×10^7 ³	0.05
Constantan	-35 ¹	2.0×10^6 ³	-
Titanium	14 ²	2.38×10^6 ³	0.01

substituting values (Table 5.1) into Equation 5.7. The equivalent Seebeck coefficient for a 0.4 μm thick copper-nickel layer was $-1 \mu\text{V}/^\circ\text{C}$ and $-17 \mu\text{V}/^\circ\text{C}$ for a 2 μm thick layer.

5.2.2. Calibration Procedure

Figure 5.5 displays the experimental apparatus. Only one sample on an oxidized wafer completed the fabrication process including wet etching of the plating base and adhesion layer. The wafer contained two sets of arrays, without an intermediate post layer. One set was with a 4 μm wire size at the junction, and the other set used a 3 μm wire size. Two 0.5 mm type-J thermocouples (model 5TC-TT-J-24-26, Omega Engineering, Inc, Stamford, CT) were fixed to the wafer with polyester tape (Harman Corporation, Rochester, MI), to monitor the temperature. One thermocouple was placed ~ 3 mm from the reference junction, near the connection to the PC board, and the other was placed ~ 3 mm from the micro-thermocouple array.

A BCS-196 cooling stage (Linkam, Ltd., UK) was used to control the temperature of the device. The cooling stage had a recessed cooling element that could not make direct contact with the bottom of the wafer. The cooling element was easily scratched, so rather than using a thermally conductive block to conduct heat from the cooling element to the wafer, a 13 mm thick PMMA block (0.17 W/mK) was used. This gave more stable results than leaving an air gap between the wafer and the cooling element. The experiments were run with a temperature range from 20 $^\circ\text{C}$ to 5 $^\circ\text{C}$, as lower temperatures were not achieved. Only one thermocouple from the array could be calibrated at a time

Figure 5.5. (a), (b) The experimental apparatus.

because of the design of the instrumentation. Two thermocouples from each of the arrays were tested to check functionality.

The samples were cooled at approximately $0.5\text{ }^{\circ}\text{C}/\text{min}$, and the temperature at the reference and measuring junctions was recorded along with the voltage output from the micro thermocouple. Measurements were taken for the samples going both up and down scale with respect to temperature. In order to distinguish between voltage generated by the reference junction compensation

thermocouple and the microthermocouple, a control case was also tested. The cooling rate was applied with the same system, but the gold-fingered pads on the PC board were offset so that they did not make contact with any of the thermocouple junctions. This provided data for the reference junction compensation thermocouple by itself, for comparison with the microthermocouple array results.

5.2.3. Calibration Results

Figure 5.6 displays the results of the control experiment. This is the plot of the measured voltage with respect to temperature at the reference junction. A least squares approximation was used to obtain the sensitivity of the reference

Figure 5.6. (a) Calibration curve recorded during cooling of the device. (b) Calibration curve recorded during heating of the device.

thermocouple. The sensitivity obtained for the cooling curve was $-11.40 \text{ mV/}^{\circ}\text{C}$ and $-10.26 \text{ mV/}^{\circ}\text{C}$ for the heating curve, indicating a difference of 10% between the two values. The standard deviation of the data from the linear fit was 6.5 mV for the cooling curve and 7.1 mV for the heating curve.

Individual thermocouples from the two arrays were tested, with data recorded for both cooling and heating. The procedure was to subtract the fitted control curve from the micro thermocouple data to obtain an estimate of the voltage generated by the microthermocouples alone. The corrected voltage was based on the difference in temperature between the measured and reference junctions. The temperatures measured at the reference junction and the measuring junction varied during the data gathering, though not regularly. This variation was used to analyze the sensitivity of the microthermocouples.

Figure 5.8 are data collected for thermocouple 8 in the $4 \mu\text{m}$ wiring layer array (Figure 5.7), shown as a representative example of the analysis process. All of the data are found in Appendix B. Figure 5.8a displays the temperature variation with respect to sample number. This is the differential temperature between the reference and the measuring junction.

Figure 5.7. Thermocouple numbering. (a) $3 \mu\text{m}$ wiring layer. (b) $4 \mu\text{m}$ wiring layer

Figure 5.8. Data curves for selected 5 μm thermocouple. a. Temperature variation between reference and measuring junction. Data is split into two curves, 1 and 2. b. Measured potential adjusted with data from control curve. c. Sensitivity plot for curve 1. d. sensitivity plot for curve 2.

The temperature profile shows a curve with both decreasing temperature and increasing temperature. The results were therefore split into two curves, one for temperature decrease (curve 1) and one for increase (curve 2), to facilitate further analysis. Figure 5.8b displays the measured potential after subtracting the data obtained from the control case, yielding just the voltage generated by the microthermocouples between the measuring and reference junctions. The two graphs were combined based on sample number to display voltage with respect to temperature difference for curves 1 and 2 (Figure 5.8c and d). A linear curve fit was applied to the data to obtain an estimate of the sensitivity for the

thermocouple. There was a possibility of error generated by subtracting a 2 V bias from the measurement and then analyzing data on the order of 10 mV.

A total of two thermocouples from each array (3 μm and 4 μm wiring) were analyzed, with both cooling and heating curves for each. A summary of the data is presented in Table 5.2. The data varied significantly between experiments. Standard deviation of data from the linear fit was in some cases as high as 200 mV, and the sensitivity between curves varied greatly. A preamplification sensitivity, Seebeck coefficient, was calculated for the thermocouples based on the amplification used with the reference junction compensation thermocouples. Data for each individual thermocouple should yield the same Seebeck coefficient, however, the values fluctuated greatly. For example, one of the thermocouples tested showed a variation from +135 to -48 $\mu\text{V}/^\circ\text{C}$ for the Seebeck coefficient.

5.2.3. Conclusions

The calibration and testing of the device was inconclusive. A standard sensitivity value for the thermocouples, meaning an actual calibration of the

Table 5.2. Results of the calibration experiments.

Thermocouple wire size	Cycle	Curve	Standard deviation, data & linear fit (mV)	Sensitivity (mV/ $^\circ\text{C}$)	Sensitivity pre-amplification ($\mu\text{V}/^\circ\text{C}$)
3 μm	cooling	1	69.2	-32.6	-114
	heating	1	8.7	-11.8	-41
		2	134.7	-60.8	-213
3 μm	cooling	1	238.8	63.9	224
		2	298.2	135.0	473
	heating	1	8.7	-31.0	-108
		2	86.7	-48.0	-168
4 μm	cooling	1	46.9	-4.6	-16
	heating	1	75.4	-44.1	-155
		2	9.0	-16.4	-58
4 μm	cooling	1	39.6	-28.0	-98
		2	31.0	-25.0	-88
	heating	1	75.4	-38.6	-135
		2	21.9	-25.4	-89

device, was unsuccessful, because of the large differences in measured values. The results do indicate a variation of voltage with respect to temperature, indicating that the micro-thermocouple junctions are providing a voltage, however this voltage has not been accurately tested. More experiments are required for conclusive results, including determining if some of the discrepancy in Seebeck coefficients is due to nonuniformity in wire composition.

The experiment could be improved upon. Proper cooling from the stage is essential. The cooling power from the cooling stage was not well regulated on the sample, and the rate was not uniform. The thermocouples used to test the device should have been smaller than the ones used. The size used was 0.5 mm, and sizes as small as 0.0127 mm are commercially available, though extremely delicate. A thermally conductive paste would help to ensure that the measurements made by the testing thermocouples would be closer to the actual temperatures for the reference and measuring junctions. Proper, repeatable placement of the thermocouples is also important.

A method to locally cool the center thermocouples would also be beneficial. The base of the wafer was cooled and any difference in the temperature between the reference and measuring junctions was not easily predictable or controllable. In order to quantify the thermopower of the micro-thermocouples, it is imperative to be able to isolate the two values from each other.

6. Conclusions and Future Work

6.1. Modeling

6.1.1 Conclusions

The thermal system was modeled at the microthermocouple level. The goal of this modeling was to determine which thermocouple geometry and spacing provided the best signal of the cellular temperature rise, and yielded the least interference between adjacent thermocouples.

Thermocouple geometries were tested with and without an intermediate post layer, with the goal of the post layer to isolate the thermocouple junction from the high thermal conductivity and large area of the wiring layer. Alternative thermocouple geometries were characterized based on the performance relative to a control system, without thermocouples. Post sizes of 3 μm and 5 μm in diameter were modeled with heights of 20 μm and 50 μm , and compared to the case without posts.

Results showed that post sizes of 3 μm in diameter provided a smaller decrease in temperature from the control than the no post case, with the 50 μm post providing the best results. The results of the 5 μm diameter posts showed an increase in the amount of heat drawn away from the cell compared to the no post case. The 50 μm tall post actually displayed a greater decrease in temperature from the control than the 20 μm post. This indicated that the larger post size drew more heat away than close cellular proximity to the wiring layer. The conclusions drawn from these experiments were that tall and thin posts provide the most favorable signal response.

The effect of thermocouple geometry on adjacent thermocouple heat transfer response was also tested. When a cell froze above a thermocouple, the goal was to minimize the measured temperature increase at adjacent thermocouples. Testing showed that there was minimal response at adjacent thermocouples for all of the cases. The adjacent response was tested with different thermocouple center to center spacings of 45 μm , 50 μm , and 55 μm . Larger spacing yielded slightly lower adjacent response.

The effect of cell location between thermocouple junctions was modeled for the same three levels of center to center spacing. The proximity to the primary thermocouple junction strongly aided in minimizing adjacent thermocouple response. The 45 μm spacing was most favorable in that respect. The limitation of fabrication capabilities meant that 45 μm spacing was also the smallest allowable size because smaller spacing creates difficulty in keeping wires electrically isolated.

6.1.2 Future Work

Simple mesh and time step refinement were done to give confidence in results. Mesh refinement was based on refining the nodes in the volume of the model cell only. To increase confidence in the results, mesh refinement over the entire system should be performed.

The effect of post sizes greater than 50 μm high should be investigated. It would be beneficial to know how the trends continue, and how close the thermocouple measured temperature can get to the undisturbed cellular system. Modeling of nanowires for the post layer would also be beneficial to determine if

this could be a possible solution to the problem of high heat transfer by the thermocouples from the cell.

The effect of different size cells could also be modeled, along with the effects of several cells, rather than the single cell used in the model. Testing the effect of partial ice formation in the cell medium would give useful data, as ice formation in the medium can cause significant differences in the measured temperature.

6.2. Fabrication

6.2.1 Conclusions

Two different sizes of thermocouples, with post sizes of 3 μm and 5 μm were fabricated. A working microthermocouple with an intermediate post layer was not successfully fabricated, although fabrication of an array without posts was completed and tested. One thermocouple junction with posts was fabricated, but the resistivity of the wafer below was too small, yielding a device that was unusable because of current leakage through the substrate.

The fabrication process was difficult to complete. The multilayer process left much room for error, and the tolerances required high optimization. One area of difficulty that was not yet optimized was with the junction exposure and deposition step. In order to expose the junction properly, it was first important to electrodeposit the two posts to approximately the same height, which was difficult to do repeatedly, as post deposition was not always exactly uniform with deposition time. The dose of the junction exposure had to be limited, to prevent excessive etching of the area between posts during development. The smallest

possible dose was also limited to ensure that the surface of the copper-nickel post was properly developed. Though the junction layer was intended to be 2 μm thick, the same thickness as the wiring layer, the electrodeposition time took much longer. The copper junction growth between posts was very slow and nonuniform between different thermocouples.

The etching of the plating base and adhesion layer was another step that was difficult. When the resist was removed, the structures were more delicate, and special care had to be taken with the wet etching to ensure that the posts were not damaged. Being careful with the sample required slow, precise movements during etching and transferring to the DI water, however the etching had to be very quick to prevent removal of the copper layer, and etching under the wires. This made the procedure difficult. The poor adhesion between the copper nickel posts and copper nickel wiring led to several debonded posts during the etching step. It is possible that a completed junction layer would reduce this problem.

6.2.2 Future Work

The additional application of SU-8 to stabilize the structure and provide a base on which cells can rest was not completed, though it may be beneficial to instead modify the fabrication process so the resist does not need to be removed. It may be possible to etch the silicon wafer from the backside, without removing the resist surrounding the thermocouple junctions, although there are other complications involved with this method, such as the high temperature needed for Si etching and requiring a temporary supporting structure on top of the resist.

Another solution may be to separate the wiring layer and post layer, and fabricate them separately, and then passively align and assemble them. With this method, electrodeposition can actually proceed in the reverse order, with the junctions plated first and then the posts plated on top. The device could then be removed from the plating base and inverted and united to the separate wiring layer.

The actual composition of the copper-nickel posts fabricated through electrodeposition needs to be characterized; time prevented it in this work. Greater post heights can also be attempted. From the work done by Yoon, et al. (1998), they were able to reach 90 μm with a single coat of positive resist. It is possible to try X-ray exposures in PMMA for taller structures as well.

The ultimate goal for this device is to combine thermoelectric coolers with the thermocouples to allow local, controlled cooling of individual cells in a culture. The fabrication process must be optimized to include both sets of structures.

6.3. Calibration and Testing

6.3.1 Conclusions

A microthermocouple array without an intermediate post layer was calibrated and tested, however the data obtained were inconclusive. A standard sensitivity value for the thermocouples was not determined. The uncertainty of the data collected was too large to determine how much of the error was based on nonuniformity of wire composition. The results did indicate a variation of voltage with respect to temperature, indicating that there is at least some effect generated by the micro-thermocouple junctions.

6.3.2 Future Work

Testing of the device could be improved upon. Improving the thermal contact with the base of the wafer to the cooling stage to make it more uniform and controllable is important. Using smaller testing thermocouples to measure reference and measuring junction temperatures, and thermally conductive bonding paste would improve the temperature reading from the testing thermocouples.

A method to locally cool the center thermocouples would be beneficial. The best way to provide a local temperature input would be to test the device on actual cells. The suitability of the device to measure cell temperature increase due to freezing was something that was not yet tested. This should be done and compared with the modeling results.

References

ASTM Committee E-20 on Temperature Measurement. *Manual on the use of thermocouples in temperature measurement*. (1970).

Bakonyi I., Toth-Kadar E., Toth J., Becsei T., Tarnoczi T. and Kamasa P. "Magnetic and electrical transport properties of electrodeposited Ni-Cu alloys and Ni₈₁Cu₁₉/Cu multilayers." *Journal of Physics Condensed Matter*. V.11 (1999) pp.963-973.

Bischof, J.C. "Quantitative measurement and prediction of biophysical response during freezing in tissues." *Annual Reviews in Biomedical Engineering*. V.2 (2000) pp.257-88.

Bischof J.C. and Rubinsky B. "Microscale heat and mass transfer of vascular intracellular freezing in the liver." *ASME Journal of Heat Transfer*. V.115 (1993) pp.1029-1035.

Chassaing K., Quang V. and Wiat R. "Kinetics of Copper Electrodeposition in Citrate Electrolytes." *Journal of Applied Electrochemistry*. V.16, n.4 (1996) pp.591- 604.

Choi Y.S. and Kang T. "Three-dimensional calculation of current distribution in electrodeposition on patterned cathode with auxiliary electrode." *Journal of the Electrochemical Society*. V.143, n.2, February (1996) pp.480-485.

Cordero N., West J. and Berney H. "Thermal management of a joule-heating microreactor using modeling tools." *ESim '04 Proceedings*, Vancouver. June (2004).

De Freitas R.C., Diller K.R., Lachenbruch C.A. and Merchant F.A. "Network thermodynamic model of coupled transport in a multicellular tissue—the islet of Langerhans." *Annals of the New York Academy of Sciences*. V.858 (1998) pp.191-205.

Delatorre R.G., Sartorelli M.L., Schervenski A.Q. and Pasa A.A. "Thermoelectric properties of electrodeposited CuNi alloys on Si." *Journal of Applied Physics*. V.93, n.10, May (2003) pp.6154-6158.

Devireddy R.V. and Bischof J.C. "Measurement of water transport during freezing in mammalian liver tissue: II. Using a differential scanning calorimeter." *Journal of Biomechanical Engineering*. V.120 (1998) pp.559-69.

Devireddy R.V. and Bischof J.C. "Recent advances in cryobiology using calorimetry" in *Low Temperature and Cryogenic Refrigeration*, ed. by Kakac S., Smirnov H., and Mila M.R. Kluwer Academic Publishers. V.99 (2003) pp.265-294.

Devireddy R.V., Smith D.J. and Bischof J.C. "Effects of microscale mass transport and phase change on numerical prediction of freezing in biological tissues." *Journal of Heat Transfer*. V.124, April (2002) pp.365-74.

Diller, K.R. "Engineering-based contributions in cryobiology." *Cryobiology*. V.34 (1997) pp.304-14.

Diller, K.R. and Cravalho E.G. "A cryomicroscope for the study of freezing and thawing processes in biological cells." *Cryobiology*. V.7 (1970) pp.191-199.

Drake P., ed. *Dimensioning & Tolerancing Handbook*. McGraw-Hill. (1999).

Fuller B.J., Busza A.L. and Proctor E. "Studies on cryoprotectant equilibration in the intact rat liver using nuclear magnetic resonance spectroscopy: a non-invasive method to assess distribution of dimethyl sulfoxide in tissues." *Cryobiology*. V.26 (1989) pp.112-18.

Goldstein R.J., Chen P.H. and Chiang H.D. "Measurement of temperature and heat transfer." in *Handbook of Heat Transfer*. ed. by Rohsenow W.M., Hartnett J.P., and Cho Y.I. McGraw Hill, 3rd ed. (1998).

Green T.A., Russell A.E. and Roy S. "The development of a stable citrate electrolyte for the electrodeposition of copper-nickel alloys." *Journal of the Electrochemical Society*. V.145, n.3, March (1998) pp.875-881.

Gualous H., Louahlia-Gualous H. and Bocus S. "Realization and thermal characterization of thin-film optothermal microsensor." *The European Physical Journal Applied Physics*. V.14, n.2 (2001) pp.147-152.

Herin P.H. and Thery P. "Measurements on the thermoelectric properties of thin layers of two metals in electrical contact. Application for designing new heat-flow sensors." *Measurement Science and Technology*. V.3, n.5 (1992) pp.495-500.

Hobbs P.V. *Ice Physics*. Oxford University Press. (1975).

Horowitz P. and Hill W. *The Art of Electronics*. Cambridge University Press. (1985).

Incropera F.P. and DeWitt D.P. *Introduction to Heat Transfer*. John Wiley and Sons, 3rd ed. (1996).

Irimia D. and Karlsson J.O.M. "Kinetics and mechanism of intercellular ice propagation in a micropatterned tissue construct." *Biophysical Journal*. V.82 (2002) pp.1858-1868.

Isbell S.A., Fyfe C.A., Ammons R.L. and Pearson B. "Measurement of cryoprotective solvent penetration into intact organ tissues using high-field NMR microimaging. *Cryobiology*. V.35 (1997) pp.165-72.

Kandra D. and Devireddy R.V. "On the possible application of a microscale thermocouple to measure intercellular ice formation in cells embedded in an extracellular matrix." *Proceedings of IMECE* (2004).

Karlsson J.O.M., Cravalho E.G. and Toner M. "A model of diffusion-limited ice growth inside biological cells during freezing." *Journal of Applied Physics*. V.75, n.9 (1994) pp.4442-55.

Levin R.L., Cravalho E.G. and Huggins C.E. "A membrane model describing the effect of temperature on the water conductivity of erythrocyte membranes at subzero temperatures." *Cryobiology*. V.13. (1976) pp.415-429.

Lovelock J.E. "The mechanism of the cryoprotective effect of glycerol against haemolysis by freezing and thawing." *Biochimica et Biophysica Acta*. V.10 (1953) p.414.

Luo K., Shi Z., Lai J. and Majumdar A. "Nanofabrication of sensors on cantilever probe tips for scanning multiprobe microscopy." *Applied Physics Letters*. V.68 (1996) pp.325-327.

MacDonald, D.K.C. *Thermoelectricity: An Introduction to the Principles*. John Wiley and Sons. (1962).

Madore C. and Landolt D. "The rotating cylinder hull cell: design and application." *Plating and Surface Finishing*. V.80, n.11, November (1993) pp. 73-78.

Madou M.J. *Fundamentals of Microfabrication: The science of Miniaturization*. CRC Press, 2nd ed. (2002).

Mehdizadeh S., Dukovic J.O., Andricacos P.C., Romankiw L.T. and Cheh H.Y. "The influence of lithographic patterning on current distribution: A model for microfabrication by electrodeposition." *Journal of the Electrochemical Society*. V.139, n.1, January (1992) pp.78-91.

Mazur, Peter. "Cryobiology: the freezing of biological systems." *Science*. V.168, Issue 3934 (1970) pp. 939-49.

Mazur, Peter. "Freezing of living cells: mechanisms and implications." *American Journal of Physiology*. V.247 (1984) pp.C125-42.

Mazur, Peter. "The role of cell membranes in the freezing of yeast and other single cells." *Annals of the New York Academy of Sciences*. V.125 (1965) pp.658-676.

Mazur, Peter. "Kinetics of water loss from cells at subzero temperatures and the likelihood of intracellular freezing." *The Journal of General Physiology*. V.47 (1963) pp.347-369.

Menz L.J., and Luyet B.J. "An electron microscope study of the distribution of ice in single muscle fibers frozen rapidly." *Biodynamica*. V.8, August (1961) p.261-294.

Nakabeppu O. and Suzuki T. "Microscale temperature measurement by scanning thermal microscopy." *Journal of Thermal Analysis and Calorimetry*. V.69 (2002) pp.727-737.

Oh Y.J., Chung S.H. and Lee M.S. "Optimization of thickness uniformity in electrodeposition onto a patterned substrate." *Materials Transactions*. V.45, n.10. (2004) pp.3005-10.

Organ Procurement and Transplant Network, Scientific Registry for Transplant Recipients. Annual Report. (2004) <http://www.ustransplant.org>.

Panda, Amrit. *Electrodeposition of Nickel-Copper Alloys and Nickel-Copper-Alumina Nanocomposites into Deep Recesses for MEMS*. PhD. Dissertation, Louisiana State University. April (2004).

Park J.J. and Taya M. "Micro-temperature sensor array with thin-film thermocouples." *Electronics Letters*. V.40, n.10 (2004) pp.599-601.

Pazhayannur P.V. and Bischof J.C. "Measurement and simulation of water transport during freezing in mammalian liver tissue." *Journal of Biomechanical Engineering*. V.119, August (1997) pp.269-277.

Pitt, R.E. "Thermodynamics and intracellular ice formation." In *Advances in Low-Temperature Biology*, ed. by Steponkus P. Elsevier Science, Ltd. V.1 (1992) pp.63-99.

Podlaha E.J., Bonhote C.H., Landolt D. "A mathematical model and experimental study of the electrodeposition of Ni-Cu alloys from complexing electrolytes." *Electrochimica Acta*. V.39, n.18 (1994) pp.2649-2657.

Rubinsky B. and Pegg D.E. "A mathematical model for the freezing process in biological tissue." *Proceedings of the Royal Society of London. Series B, Biological Sciences.* V.234, n.1276 (1988) pp.343-58.

Rubinsky B., Gilbert J.C., Onik G.M., Roos M.S., Wong S.T.S. and Brennan K.M. "Monitoring cryosurgery in the brain and in the prostate with proton NMR." *Cryobiology.* V.30 (1993) pp.191-99.

Shi L. and Majumdar A. "Recent developments in micro and nanoscale thermometry." *Microscale Thermophysical Engineering.* V.5 (2001) pp.251-265.

Shi L., Kwon O., Miner A.C. and Majumdar A. "Design and batch fabrication of probes for sub-100 nm scanning thermal microscopy." *Journal of Microelectromechanical Systems.* V.10, n.3 (2001) pp.370-378.

Sinclair, G. "Finite element applications in mechanical engineering." Course at Louisiana State University. Fall (2004).

Tacke J., Speetzen R., Heschel I., Hunter D.W., Rau G. and Günther R.W. "Imaging of interstitial cryotherapy—an in vitro comparison of ultrasound, computed tomography, and magnetic resonance image." *Cryobiology.* V.38 (1999) pp.250-59.

Taherian H. and Hosseini R. "Electroplating technique as a method for manufacturing copper-constantan thermocouples." *Amirkabir, Journal of Science and Technology.* V.15, n.57B (2004) pp.11-15.

Toner M., Cravalho E.G. and Karel M. "Thermodynamics and kinetics of intracellular ice formation during freezing of biological cells." *Journal of Applied Physics.* V.67 (1990) pp.1582-93. Erratum: V.70 (1991) pp.4653.

Walcerz D.B. and Diller K.R. "Quantitative light microscopy of combined perfusion and freezing processes." *Journal of Microscopy.* V.161 (1991) pp.297-311.

Williams C.C. and Wickramasinghe H.K. "Scanning thermal profiler." *Applied Physics Letters.* V.49 (1986) pp.1587-1589.

Worner H.W. "Thermoelectric properties of titanium with special reference to the allotropic transformation." *Australian Journal of Scientific Research.* V.4, n.1 (1960) pp.62-83.

Yoon J.B., Han C.H., Yoon E. and Kim C.K. "Novel two-step baking process for high-aspect-ratio photolithography with conventional positive thick photoresist." *Proceedings of SPIE, Materials and Device Characterization in Micromachining.* V.3512, September (1998) pp.316-325.

“Constantan.” wikkipedia.org. <http://en.wikipedia.org/wiki/Constantan>. March, 2006.

“Copper.” wikkipedia.org. <http://en.wikipedia.org/wiki/Copper>. March, 2006.

“Polymethylmethacrylate (PMMA, Acrylic)-Material Information.” Goodfellow.com. <http://www.goodfellow.com/csp/active/static/A/Polymethylmethacrylate.html>. December, 2005.

“Thermocouples: Theory.” Efunda.com. http://efunda.com/designstandards/sensors/thermocouples/thmcple_theory.cfm. February, 2006.

“Titanium.” wikkipedia.org. <http://en.wikipedia.org/wiki/Titanium>. February, 2006.

Appendix A: Photomasks Used in Microfabrication

Figure A1. Layer 1 UV photomask (copper wiring layer). All masks fit 4 inch Si wafers.

Figure A2. Layer 1 photomask, detail view of center.

Figure A3. Layer 2 UV photomask (constantan wiring layer).

Figure A4. Layer 2 photomask, detail view of center.

Figure A5. Layer 3 UV photomask (copper post layer).

Figure A6. Layer 3 photomask, detail view of center.

Figure A7. Layer 4 UV photomask (constantan post layer).

Figure A8. Layer 4 photomask, detail view of center.

Figure A9. Layer 5 UV photomask (copper junction layer).

100 μ m

Figure A10. Layer 5 photomask, detail view of center.

Appendix B: Microthermocouple Testing Results

Figure B1. Thermocouple numbering for identifying testing results. (a) 3 μm wiring layer. (b) 4 μm wiring layer

Figure B2. Data collected for thermocouple 3 of the 3 μm array, during the cooling cycle. (a) Temperature difference between measuring and reference junction plotted against sample number. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot.

Figure B3. Data collected for thermocouple 3 of the 3 μm array, during the heating cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Figure B4. Data collected for thermocouple 5 of the 3 μm array, during the cooling cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Figure B5. Data collected for thermocouple 5 of the 3 μm array, during the heating cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Figure B6. Data collected for thermocouple 1 of the 4 μm array, during the cooling cycle. (a) Temperature difference between measuring and reference junction plotted against sample number. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot.

Figure B7. Data collected for thermocouple 1 of the 4 μm array, during the heating cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Figure B8. Data collected for thermocouple 6 of the 4 μm array, during the cooling cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Figure B9. Data collected for thermocouple 6 of the 4 μm array, during the heating cycle. (a) Temperature difference between measuring and reference junction plotted against sample number, separated into curve 1 and 2. (b) Voltage generated between measuring and reference junction, plotted against sample number. (c) Calibration plot for curve 1. (d) Calibration plot for curve 2.

Appendix C: Circuit Diagram

Figure C1. Top left section of the circuit diagram.

Figure C2. Top right section of the circuit diagram.

Figure C3. Bottom left section of the circuit diagram.

Figure C4. Bottom right section of the circuit diagram.

Vita

Adam Cygan was born in Wroclaw, Poland, on February 29th, 1980. Two years later, his family moved to the United States when his father took a job as a math professor at Louisiana State University. They lived in Baton Rouge, Louisiana, where Adam attended school and graduated from Baton Rouge Magnet High in 1998. He finished his undergraduate studies in mechanical engineering at Louisiana State University in 2002, and then went on to pursue a master's degree there, in the same field. He received a job with Schlumberger, and will be moving to Houston to begin work in March 2006.